

DMX CHART



www.chauvetprofessional.com

DMX Values

STD.P

| Channel | Function | Value | Percent/Setting |
|-----------|---------------------------------|-----------|------------------------------------|
| 1 | Dimmer | 000 ⇄ 255 | 0-100% |
| 2 | Fine Dimmer | 000 ⇄ 255 | Fine control (16-bit) |
| 3 | Shutter | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect from slow to fast |
| | | 180 ⇄ 189 | No function |
| 190 ⇄ 255 | Random effect from slow to fast | | |
| 4 | Zoom | 000 ⇄ 255 | Narrow-wide |
| 5 | Zoom Motor Reset | 000 ⇄ 200 | No function |
| | | 201 ⇄ 220 | Zoom motor reset |
| | | 221 ⇄ 255 | No function |

DOS

| Channel | Function | Value | Percent/Setting |
|---------|-------------|-----------|-----------------------|
| 1 | Dimmer | 000 ⇄ 255 | 0-100% |
| 2 | Fine Dimmer | 000 ⇄ 255 | Fine control (16-bit) |

UNO

| Channel | Function | Value | Percent/Setting |
|---------|----------|-----------|-----------------|
| 1 | Dimmer | 000 ⇄ 255 | 0-100% |