

COLORado Batten Q15

Color Macro Chart

| DMX Channel Value | Red Value | Green Value | Blue Value | White Value |
|-------------------|-------------|-------------|-------------|-------------|
| 000 ⇄ 010 | No function | No function | No function | No function |
| 011 ⇄ 034 | 100% | 0–100% | 0% | 0% |
| 035 ⇄ 059 | 100–0% | 100% | 0% | 0% |
| 060 ⇄ 084 | 0% | 100% | 0–100% | 0% |
| 085 ⇄ 109 | 0% | 100–0% | 100% | 0% |
| 110 ⇄ 134 | 0–100% | 0% | 100% | 0% |
| 135 ⇄ 159 | 100% | 0% | 100–0% | 0% |
| 160 ⇄ 184 | 100% | 0–100% | 0–100% | 0% |
| 185 ⇄ 209 | 100–0% | 100–0% | 100% | 0% |
| 210 ⇄ 255 | 100% | 100% | 100% | 100% |

Color Temperature Chart

| DMX Channel Value | Color Temperature |
|-------------------|-------------------|
| 000 ⇄ 010 | No function |
| 011 ⇄ 028 | 1800K |
| 029 ⇄ 046 | 2200K |
| 047 ⇄ 064 | 2700K |
| 065 ⇄ 082 | 3000K |
| 083 ⇄ 100 | 3200K |
| 101 ⇄ 118 | 3500K |
| 119 ⇄ 136 | 4000K |
| 137 ⇄ 154 | 4200K |
| 155 ⇄ 172 | 4500K |
| 173 ⇄ 190 | 5600K |
| 191 ⇄ 208 | 6000K |
| 209 ⇄ 226 | 6500K |
| 227 ⇄ 244 | 7200K |
| 245 ⇄ 255 | 8000K |

 The color temperatures above are simulated renditions of the color output produced as compared to a tungsten lamp at the specified color temperature. Chauvet makes no guarantee of the color output accuracy.

15-Cell DMX Values
15 HSIC (76 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|--------------|-----------|--------------------------------|
| 1 | Dimmer 1 | 000 ⇄ 255 | 0–100% |
| 2 | Hue 1 | 000 ⇄ 255 | 0–100% |
| 3 | Fine Hue 1 | 000 ⇄ 255 | 0–100% |
| 4 | Saturation 1 | 000 ⇄ 255 | 0–100% |
| 5 | Strobe 1 | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 6 | Dimmer 2 | 000 ⇄ 255 | 0–100% |
| 7 | Hue 2 | 000 ⇄ 255 | 0–100% |
| 8 | Fine Hue 2 | 000 ⇄ 255 | 0–100% |
| 9 | Saturation 2 | 000 ⇄ 255 | 0–100% |
| 10 | Strobe 2 | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 11 | Dimmer 3 | 000 ⇄ 255 | 0–100% |
| 12 | Hue 3 | 000 ⇄ 255 | 0–100% |
| 13 | Fine Hue 3 | 000 ⇄ 255 | 0–100% |
| 14 | Saturation 3 | 000 ⇄ 255 | 0–100% |
| 15 | Strobe 3 | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 16 | Dimmer 4 | 000 ⇄ 255 | 0–100% |
| 17 | Hue 4 | 000 ⇄ 255 | 0–100% |
| 18 | Fine Hue 4 | 000 ⇄ 255 | 0–100% |
| 19 | Saturation 4 | 000 ⇄ 255 | 0–100% |
| 20 | Strobe 4 | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 21 | Dimmer 5 | 000 ⇄ 255 | 0–100% |
| 22 | Hue 5 | 000 ⇄ 255 | 0–100% |
| 23 | Fine Hue 5 | 000 ⇄ 255 | 0–100% |
| 24 | Saturation 5 | 000 ⇄ 255 | 0–100% |
| 25 | Strobe 5 | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 26 | Dimmer 6 | 000 ⇄ 255 | 0–100% |
| 27 | Hue 6 | 000 ⇄ 255 | 0–100% |
| 28 | Fine Hue 6 | 000 ⇄ 255 | 0–100% |

QUICK REFERENCE GUIDE



COLORado Batten Q15

| Channel | Function | Value | Percent/Setting |
|---------|---------------|-----------|--------------------------------|
| 29 | Saturation 6 | 000 ⇔ 255 | 0–100% |
| 30 | Strobe 6 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 31 | Dimmer 7 | 000 ⇔ 255 | 0–100% |
| 32 | Hue 7 | 000 ⇔ 255 | 0–100% |
| 33 | Fine Hue 7 | 000 ⇔ 255 | 0–100% |
| 34 | Saturation 7 | 000 ⇔ 255 | 0–100% |
| 35 | Strobe 7 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 36 | Dimmer 8 | 000 ⇔ 255 | 0–100% |
| 37 | Hue 8 | 000 ⇔ 255 | 0–100% |
| 38 | Fine Hue 8 | 000 ⇔ 255 | 0–100% |
| 39 | Saturation 8 | 000 ⇔ 255 | 0–100% |
| 40 | Strobe 8 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 41 | Dimmer 9 | 000 ⇔ 255 | 0–100% |
| 42 | Hue 9 | 000 ⇔ 255 | 0–100% |
| 43 | Fine Hue 9 | 000 ⇔ 255 | 0–100% |
| 44 | Saturation 9 | 000 ⇔ 255 | 0–100% |
| 45 | Strobe 9 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 46 | Dimmer 10 | 000 ⇔ 255 | 0–100% |
| 47 | Hue 10 | 000 ⇔ 255 | 0–100% |
| 48 | Fine Hue 10 | 000 ⇔ 255 | 0–100% |
| 49 | Saturation 10 | 000 ⇔ 255 | 0–100% |
| 50 | Strobe 10 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 51 | Dimmer 11 | 000 ⇔ 255 | 0–100% |
| 52 | Hue 11 | 000 ⇔ 255 | 0–100% |
| 53 | Fine Hue 11 | 000 ⇔ 255 | 0–100% |
| 54 | Saturation 11 | 000 ⇔ 255 | 0–100% |

| Channel | Function | Value | Percent/Setting |
|---------|---------------|-----------|---------------------------------------|
| 55 | Strobe 11 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 56 | Dimmer 12 | 000 ⇔ 255 | 0–100% |
| 57 | Hue 12 | 000 ⇔ 255 | 0–100% |
| 58 | Fine Hue 12 | 000 ⇔ 255 | 0–100% |
| 59 | Saturation 12 | 000 ⇔ 255 | 0–100% |
| 60 | Strobe 12 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 61 | Dimmer 13 | 000 ⇔ 255 | 0–100% |
| 62 | Hue 13 | 000 ⇔ 255 | 0–100% |
| 63 | Fine Hue 13 | 000 ⇔ 255 | 0–100% |
| 64 | Saturation 13 | 000 ⇔ 255 | 0–100% |
| 65 | Strobe 13 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 66 | Dimmer 14 | 000 ⇔ 255 | 0–100% |
| 67 | Hue 14 | 000 ⇔ 255 | 0–100% |
| 68 | Fine Hue 14 | 000 ⇔ 255 | 0–100% |
| 69 | Saturation 14 | 000 ⇔ 255 | 0–100% |
| 70 | Strobe 14 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 71 | Dimmer 15 | 000 ⇔ 255 | 0–100% |
| 72 | Hue 15 | 000 ⇔ 255 | 0–100% |
| 73 | Fine Hue 15 | 000 ⇔ 255 | 0–100% |
| 74 | Saturation 15 | 000 ⇔ 255 | 0–100% |
| 75 | Strobe 15 | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |
| 76 | Dimmer Speed | 000 ⇔ 009 | Preset dimmer speed from display menu |
| | | 010 ⇔ 029 | Dimmer speed mode off |
| | | 030 ⇔ 069 | Dimmer speed mode 1 (fastest) |
| | | 070 ⇔ 129 | Dimmer speed mode 2 |
| | | 130 ⇔ 189 | Dimmer speed mode 3 |
| | | 190 ⇔ 255 | Dimmer speed mode 4 (slowest) |

QUICK REFERENCE GUIDE



COLORado Batten Q15

15 Advanced (66 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|-------------|-----------|-----------------|
| 1 | Dimmer | 000 ⇔ 255 | 0–100% |
| 2 | Fine Dimmer | 000 ⇔ 255 | 0–100% |
| 3 | Red 1 | 000 ⇔ 255 | 0–100% |
| 4 | Green 1 | 000 ⇔ 255 | 0–100% |
| 5 | Blue 1 | 000 ⇔ 255 | 0–100% |
| 6 | White 1 | 000 ⇔ 255 | 0–100% |
| 7 | Red 2 | 000 ⇔ 255 | 0–100% |
| 8 | Green 2 | 000 ⇔ 255 | 0–100% |
| 9 | Blue 2 | 000 ⇔ 255 | 0–100% |
| 10 | White 2 | 000 ⇔ 255 | 0–100% |
| 11 | Red 3 | 000 ⇔ 255 | 0–100% |
| 12 | Green 3 | 000 ⇔ 255 | 0–100% |
| 13 | Blue 3 | 000 ⇔ 255 | 0–100% |
| 14 | White 3 | 000 ⇔ 255 | 0–100% |
| 15 | Red 4 | 000 ⇔ 255 | 0–100% |
| 16 | Green 4 | 000 ⇔ 255 | 0–100% |
| 17 | Blue 4 | 000 ⇔ 255 | 0–100% |
| 18 | White 4 | 000 ⇔ 255 | 0–100% |
| 19 | Red 5 | 000 ⇔ 255 | 0–100% |
| 20 | Green 5 | 000 ⇔ 255 | 0–100% |
| 21 | Blue 5 | 000 ⇔ 255 | 0–100% |
| 22 | White 5 | 000 ⇔ 255 | 0–100% |
| 23 | Red 6 | 000 ⇔ 255 | 0–100% |
| 24 | Green 6 | 000 ⇔ 255 | 0–100% |
| 25 | Blue 6 | 000 ⇔ 255 | 0–100% |
| 26 | White 6 | 000 ⇔ 255 | 0–100% |
| 27 | Red 7 | 000 ⇔ 255 | 0–100% |
| 28 | Green 7 | 000 ⇔ 255 | 0–100% |
| 29 | Blue 7 | 000 ⇔ 255 | 0–100% |
| 30 | White 7 | 000 ⇔ 255 | 0–100% |
| 31 | Red 8 | 000 ⇔ 255 | 0–100% |
| 32 | Green 8 | 000 ⇔ 255 | 0–100% |
| 33 | Blue 8 | 000 ⇔ 255 | 0–100% |
| 34 | White 8 | 000 ⇔ 255 | 0–100% |
| 35 | Red 9 | 000 ⇔ 255 | 0–100% |
| 36 | Green 9 | 000 ⇔ 255 | 0–100% |
| 37 | Blue 9 | 000 ⇔ 255 | 0–100% |
| 38 | White 9 | 000 ⇔ 255 | 0–100% |
| 39 | Red 10 | 000 ⇔ 255 | 0–100% |
| 40 | Green 10 | 000 ⇔ 255 | 0–100% |
| 41 | Blue 10 | 000 ⇔ 255 | 0–100% |
| 42 | White 10 | 000 ⇔ 255 | 0–100% |
| 43 | Red 11 | 000 ⇔ 255 | 0–100% |
| 44 | Green 11 | 000 ⇔ 255 | 0–100% |
| 45 | Blue 11 | 000 ⇔ 255 | 0–100% |
| 46 | White 11 | 000 ⇔ 255 | 0–100% |
| 47 | Red 12 | 000 ⇔ 255 | 0–100% |
| 48 | Green 12 | 000 ⇔ 255 | 0–100% |
| 49 | Blue 12 | 000 ⇔ 255 | 0–100% |
| 50 | White 12 | 000 ⇔ 255 | 0–100% |
| 51 | Red 13 | 000 ⇔ 255 | 0–100% |
| 52 | Green 13 | 000 ⇔ 255 | 0–100% |
| 53 | Blue 13 | 000 ⇔ 255 | 0–100% |
| 54 | White 13 | 000 ⇔ 255 | 0–100% |

| Channel | Function | Value | Percent/Setting |
|---------|--------------------|-----------|---|
| 55 | Red 14 | 000 ⇄ 255 | 0–100% |
| 56 | Green 14 | 000 ⇄ 255 | 0–100% |
| 57 | Blue 14 | 000 ⇄ 255 | 0–100% |
| 58 | White 14 | 000 ⇄ 255 | 0–100% |
| 59 | Red 15 | 000 ⇄ 255 | 0–100% |
| 60 | Green 15 | 000 ⇄ 255 | 0–100% |
| 61 | Blue 15 | 000 ⇄ 255 | 0–100% |
| 62 | White 15 | 000 ⇄ 255 | 0–100% |
| 63 | Color Macros | 000 ⇄ 255 | See Color Macro Chart |
| 64 | Color Temperatures | 000 ⇄ 255 | See Color Temperature Chart |
| 65 | Strobe | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 66 | Dimmer Speed | 000 ⇄ 009 | Preset dimmer speed from display menu |
| | | 010 ⇄ 029 | Dimmer speed mode off |
| | | 030 ⇄ 069 | Dimmer speed mode 1 (fastest) |
| | | 070 ⇄ 129 | Dimmer speed mode 2 |
| | | 130 ⇄ 189 | Dimmer speed mode 3 |
| | | 190 ⇄ 255 | Dimmer speed mode 4 (slowest) |

15 Basic (64 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|-------------|-----------|-----------------|
| 1 | Dimmer | 000 ⇄ 255 | 0–100% |
| 2 | Fine Dimmer | 000 ⇄ 255 | 0–100% |
| 3 | Red 1 | 000 ⇄ 255 | 0–100% |
| 4 | Green 1 | 000 ⇄ 255 | 0–100% |
| 5 | Blue 1 | 000 ⇄ 255 | 0–100% |
| 6 | White 1 | 000 ⇄ 255 | 0–100% |
| 7 | Red 2 | 000 ⇄ 255 | 0–100% |
| 8 | Green 2 | 000 ⇄ 255 | 0–100% |
| 9 | Blue 2 | 000 ⇄ 255 | 0–100% |
| 10 | White 2 | 000 ⇄ 255 | 0–100% |
| 11 | Red 3 | 000 ⇄ 255 | 0–100% |
| 12 | Green 3 | 000 ⇄ 255 | 0–100% |
| 13 | Blue 3 | 000 ⇄ 255 | 0–100% |
| 14 | White 3 | 000 ⇄ 255 | 0–100% |
| 15 | Red 4 | 000 ⇄ 255 | 0–100% |
| 16 | Green 4 | 000 ⇄ 255 | 0–100% |
| 17 | Blue 4 | 000 ⇄ 255 | 0–100% |
| 18 | White 4 | 000 ⇄ 255 | 0–100% |
| 19 | Red 5 | 000 ⇄ 255 | 0–100% |
| 20 | Green 5 | 000 ⇄ 255 | 0–100% |
| 21 | Blue 5 | 000 ⇄ 255 | 0–100% |
| 22 | White 5 | 000 ⇄ 255 | 0–100% |
| 23 | Red 6 | 000 ⇄ 255 | 0–100% |
| 24 | Green 6 | 000 ⇄ 255 | 0–100% |
| 25 | Blue 6 | 000 ⇄ 255 | 0–100% |
| 26 | White 6 | 000 ⇄ 255 | 0–100% |
| 27 | Red 7 | 000 ⇄ 255 | 0–100% |
| 28 | Green 7 | 000 ⇄ 255 | 0–100% |
| 29 | Blue 7 | 000 ⇄ 255 | 0–100% |
| 30 | White 7 | 000 ⇄ 255 | 0–100% |

QUICK REFERENCE GUIDE



COLORado Batten Q15

| Channel | Function | Value | Percent/Setting |
|---------|--------------|-----------|---------------------------------------|
| 31 | Red 8 | 000 ⇔ 255 | 0–100% |
| 32 | Green 8 | 000 ⇔ 255 | 0–100% |
| 33 | Blue 8 | 000 ⇔ 255 | 0–100% |
| 34 | White 8 | 000 ⇔ 255 | 0–100% |
| 35 | Red 9 | 000 ⇔ 255 | 0–100% |
| 36 | Green 9 | 000 ⇔ 255 | 0–100% |
| 37 | Blue 9 | 000 ⇔ 255 | 0–100% |
| 38 | White 9 | 000 ⇔ 255 | 0–100% |
| 39 | Red 10 | 000 ⇔ 255 | 0–100% |
| 40 | Green 10 | 000 ⇔ 255 | 0–100% |
| 41 | Blue 10 | 000 ⇔ 255 | 0–100% |
| 42 | White 10 | 000 ⇔ 255 | 0–100% |
| 43 | Red 11 | 000 ⇔ 255 | 0–100% |
| 44 | Green 11 | 000 ⇔ 255 | 0–100% |
| 45 | Blue 11 | 000 ⇔ 255 | 0–100% |
| 46 | White 11 | 000 ⇔ 255 | 0–100% |
| 47 | Red 12 | 000 ⇔ 255 | 0–100% |
| 48 | Green 12 | 000 ⇔ 255 | 0–100% |
| 49 | Blue 12 | 000 ⇔ 255 | 0–100% |
| 50 | White 12 | 000 ⇔ 255 | 0–100% |
| 51 | Red 13 | 000 ⇔ 255 | 0–100% |
| 52 | Green 13 | 000 ⇔ 255 | 0–100% |
| 53 | Blue 13 | 000 ⇔ 255 | 0–100% |
| 54 | White 13 | 000 ⇔ 255 | 0–100% |
| 55 | Red 14 | 000 ⇔ 255 | 0–100% |
| 56 | Green 14 | 000 ⇔ 255 | 0–100% |
| 57 | Blue 14 | 000 ⇔ 255 | 0–100% |
| 58 | White 14 | 000 ⇔ 255 | 0–100% |
| 59 | Red 15 | 000 ⇔ 255 | 0–100% |
| 60 | Green 15 | 000 ⇔ 255 | 0–100% |
| 61 | Blue 15 | 000 ⇔ 255 | 0–100% |
| 62 | White 15 | 000 ⇔ 255 | 0–100% |
| 63 | Color Macros | 000 ⇔ 255 | See Color Macro Chart |
| 64 | Strobe | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |

15 Simple (60 Channels)

| Channel | Function | Value | Percent/Setting |
|----------------|-----------------|--------------|------------------------|
| 1 | Red 1 | 000 ⇄ 255 | 0–100% |
| 2 | Green 1 | 000 ⇄ 255 | 0–100% |
| 3 | Blue 1 | 000 ⇄ 255 | 0–100% |
| 4 | White 1 | 000 ⇄ 255 | 0–100% |
| 5 | Red 2 | 000 ⇄ 255 | 0–100% |
| 6 | Green 2 | 000 ⇄ 255 | 0–100% |
| 7 | Blue 2 | 000 ⇄ 255 | 0–100% |
| 8 | White 2 | 000 ⇄ 255 | 0–100% |
| 9 | Red 3 | 000 ⇄ 255 | 0–100% |
| 10 | Green 3 | 000 ⇄ 255 | 0–100% |
| 11 | Blue 3 | 000 ⇄ 255 | 0–100% |
| 12 | White 3 | 000 ⇄ 255 | 0–100% |
| 13 | Red 4 | 000 ⇄ 255 | 0–100% |
| 14 | Green 4 | 000 ⇄ 255 | 0–100% |
| 15 | Blue 4 | 000 ⇄ 255 | 0–100% |
| 16 | White 4 | 000 ⇄ 255 | 0–100% |
| 17 | Red 5 | 000 ⇄ 255 | 0–100% |
| 18 | Green 5 | 000 ⇄ 255 | 0–100% |
| 19 | Blue 5 | 000 ⇄ 255 | 0–100% |
| 20 | White 5 | 000 ⇄ 255 | 0–100% |
| 21 | Red 6 | 000 ⇄ 255 | 0–100% |
| 22 | Green 6 | 000 ⇄ 255 | 0–100% |
| 23 | Blue 6 | 000 ⇄ 255 | 0–100% |
| 24 | White 6 | 000 ⇄ 255 | 0–100% |
| 25 | Red 7 | 000 ⇄ 255 | 0–100% |
| 26 | Green 7 | 000 ⇄ 255 | 0–100% |
| 27 | Blue 7 | 000 ⇄ 255 | 0–100% |
| 28 | White 7 | 000 ⇄ 255 | 0–100% |
| 29 | Red 8 | 000 ⇄ 255 | 0–100% |
| 30 | Green 8 | 000 ⇄ 255 | 0–100% |
| 31 | Blue 8 | 000 ⇄ 255 | 0–100% |
| 32 | White 8 | 000 ⇄ 255 | 0–100% |
| 33 | Red 9 | 000 ⇄ 255 | 0–100% |
| 34 | Green 9 | 000 ⇄ 255 | 0–100% |
| 35 | Blue 9 | 000 ⇄ 255 | 0–100% |
| 36 | White 9 | 000 ⇄ 255 | 0–100% |
| 37 | Red 10 | 000 ⇄ 255 | 0–100% |
| 38 | Green 10 | 000 ⇄ 255 | 0–100% |
| 39 | Blue 10 | 000 ⇄ 255 | 0–100% |
| 40 | White 10 | 000 ⇄ 255 | 0–100% |
| 41 | Red 11 | 000 ⇄ 255 | 0–100% |
| 42 | Green 11 | 000 ⇄ 255 | 0–100% |
| 43 | Blue 11 | 000 ⇄ 255 | 0–100% |
| 44 | White 11 | 000 ⇄ 255 | 0–100% |
| 45 | Red 12 | 000 ⇄ 255 | 0–100% |
| 46 | Green 12 | 000 ⇄ 255 | 0–100% |
| 47 | Blue 12 | 000 ⇄ 255 | 0–100% |
| 48 | White 12 | 000 ⇄ 255 | 0–100% |
| 49 | Red 13 | 000 ⇄ 255 | 0–100% |
| 50 | Green 13 | 000 ⇄ 255 | 0–100% |
| 51 | Blue 13 | 000 ⇄ 255 | 0–100% |
| 52 | White 13 | 000 ⇄ 255 | 0–100% |
| 53 | Red 14 | 000 ⇄ 255 | 0–100% |
| 54 | Green 14 | 000 ⇄ 255 | 0–100% |

QUICK REFERENCE GUIDE



COLORado Batten Q15

| Channel | Function | Value | Percent/Setting |
|---------|----------|-----------|-----------------|
| 55 | Blue 14 | 000 ⇔ 255 | 0–100% |
| 56 | White 14 | 000 ⇔ 255 | 0–100% |
| 57 | Red 15 | 000 ⇔ 255 | 0–100% |
| 58 | Green 15 | 000 ⇔ 255 | 0–100% |
| 59 | Blue 15 | 000 ⇔ 255 | 0–100% |
| 60 | White 15 | 000 ⇔ 255 | 0–100% |

15 Pixel (45 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|----------|-----------|-----------------|
| 1 | Red 1 | 000 ⇔ 255 | 0–100% |
| 2 | Green 1 | 000 ⇔ 255 | 0–100% |
| 3 | Blue 1 | 000 ⇔ 255 | 0–100% |
| 4 | Red 2 | 000 ⇔ 255 | 0–100% |
| 5 | Green 2 | 000 ⇔ 255 | 0–100% |
| 6 | Blue 2 | 000 ⇔ 255 | 0–100% |
| 7 | Red 3 | 000 ⇔ 255 | 0–100% |
| 8 | Green 3 | 000 ⇔ 255 | 0–100% |
| 9 | Blue 3 | 000 ⇔ 255 | 0–100% |
| 10 | Red 4 | 000 ⇔ 255 | 0–100% |
| 11 | Green 4 | 000 ⇔ 255 | 0–100% |
| 12 | Blue 4 | 000 ⇔ 255 | 0–100% |
| 13 | Red 5 | 000 ⇔ 255 | 0–100% |
| 14 | Green 5 | 000 ⇔ 255 | 0–100% |
| 15 | Blue 5 | 000 ⇔ 255 | 0–100% |
| 16 | Red 6 | 000 ⇔ 255 | 0–100% |
| 17 | Green 6 | 000 ⇔ 255 | 0–100% |
| 18 | Blue 6 | 000 ⇔ 255 | 0–100% |
| 19 | Red 7 | 000 ⇔ 255 | 0–100% |
| 20 | Green 7 | 000 ⇔ 255 | 0–100% |
| 21 | Blue 7 | 000 ⇔ 255 | 0–100% |
| 22 | Red 8 | 000 ⇔ 255 | 0–100% |
| 23 | Green 8 | 000 ⇔ 255 | 0–100% |
| 24 | Blue 8 | 000 ⇔ 255 | 0–100% |
| 25 | Red 9 | 000 ⇔ 255 | 0–100% |
| 26 | Green 9 | 000 ⇔ 255 | 0–100% |
| 27 | Blue 9 | 000 ⇔ 255 | 0–100% |
| 28 | Red 10 | 000 ⇔ 255 | 0–100% |
| 29 | Green 10 | 000 ⇔ 255 | 0–100% |
| 30 | Blue 10 | 000 ⇔ 255 | 0–100% |
| 31 | Red 11 | 000 ⇔ 255 | 0–100% |
| 32 | Green 11 | 000 ⇔ 255 | 0–100% |
| 33 | Blue 11 | 000 ⇔ 255 | 0–100% |
| 34 | Red 12 | 000 ⇔ 255 | 0–100% |
| 35 | Green 12 | 000 ⇔ 255 | 0–100% |
| 36 | Blue 12 | 000 ⇔ 255 | 0–100% |
| 37 | Red 13 | 000 ⇔ 255 | 0–100% |
| 38 | Green 13 | 000 ⇔ 255 | 0–100% |
| 39 | Blue 13 | 000 ⇔ 255 | 0–100% |
| 40 | Red 14 | 000 ⇔ 255 | 0–100% |
| 41 | Green 14 | 000 ⇔ 255 | 0–100% |
| 42 | Blue 14 | 000 ⇔ 255 | 0–100% |
| 43 | Red 15 | 000 ⇔ 255 | 0–100% |
| 44 | Green 15 | 000 ⇔ 255 | 0–100% |
| 45 | Blue 15 | 000 ⇔ 255 | 0–100% |

1-Cell DMX Values

1 HSIC (6 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|--------------|-----------|---------------------------------------|
| 1 | Dimmer | 000 ⇄ 255 | 0–100% |
| 2 | Hue | 000 ⇄ 255 | 0–100% |
| 3 | Fine Hue | 000 ⇄ 255 | 0–100% |
| 4 | Saturation | 000 ⇄ 255 | 0–100% |
| 5 | Strobe | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 6 | Dimmer Speed | 000 ⇄ 009 | Preset dimmer speed from display menu |
| | | 010 ⇄ 029 | Dimmer speed mode off |
| | | 030 ⇄ 069 | Dimmer speed mode 1 (fastest) |
| | | 070 ⇄ 129 | Dimmer speed mode 2 |
| | | 130 ⇄ 189 | Dimmer speed mode 3 |
| | | 190 ⇄ 255 | Dimmer speed mode 4 (slowest) |

1 Advanced (10 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|--------------------|-----------|---|
| 1 | Dimmer | 000 ⇄ 255 | 0–100% |
| 2 | Fine Dimmer | 000 ⇄ 255 | 0–100% |
| 3 | Red | 000 ⇄ 255 | 0–100% |
| 4 | Green | 000 ⇄ 255 | 0–100% |
| 5 | Blue | 000 ⇄ 255 | 0–100% |
| 6 | White | 000 ⇄ 255 | 0–100% |
| 7 | Color Macros | 000 ⇄ 255 | See Color Macro Chart |
| 8 | Color Temperatures | 000 ⇄ 255 | See Color Temperature Chart |
| 9 | Strobe | 000 ⇄ 009 | No function |
| | | 010 ⇄ 099 | Strobe, slow to fast |
| | | 100 ⇄ 109 | No function |
| | | 110 ⇄ 179 | Lightning effect, slow to fast |
| | | 180 ⇄ 189 | No function |
| | | 190 ⇄ 255 | Random strobe, slow to fast |
| 10 | Dimmer Speed | 000 ⇄ 009 | Preset dimmer speed from display menu |
| | | 010 ⇄ 029 | Dimmer speed mode off |
| | | 030 ⇄ 069 | Dimmer speed mode 1 (fastest) |
| | | 070 ⇄ 129 | Dimmer speed mode 2 |
| | | 130 ⇄ 189 | Dimmer speed mode 3 |
| | | 190 ⇄ 255 | Dimmer speed mode 4 (slowest) |

COLORado Batten Q15

1 Basic (8 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|--------------|-----------|---------------------------------------|
| 1 | Dimmer | 000 ⇔ 255 | 0–100% |
| 2 | Fine Dimmer | 000 ⇔ 255 | 0–100% |
| 3 | Red | 000 ⇔ 255 | 0–100% |
| 4 | Green | 000 ⇔ 255 | 0–100% |
| 5 | Blue | 000 ⇔ 255 | 0–100% |
| 6 | White | 000 ⇔ 255 | 0–100% |
| 7 | Color Macros | 000 ⇔ 255 | See Color Macro Chart |
| 8 | Strobe | 000 ⇔ 009 | No function |
| | | 010 ⇔ 099 | Strobe, slow to fast |
| | | 100 ⇔ 109 | No function |
| | | 110 ⇔ 179 | Lightning effect, slow to fast |
| | | 180 ⇔ 189 | No function |
| | | 190 ⇔ 255 | Random strobe, slow to fast |

1 Simple (4 Channels)

| Channel | Function | Value | Percent/Setting |
|---------|----------|-----------|-----------------|
| 1 | Red | 000 ⇔ 255 | 0–100% |
| 2 | Green | 000 ⇔ 255 | 0–100% |
| 3 | Blue | 000 ⇔ 255 | 0–100% |
| 4 | White | 000 ⇔ 255 | 0–100% |