

DMX Values

STD.P	Channel	Function	Value	Percent/Setting
	1	Dimmer	000 ó 255	0–100%
	2	Dimmer Fine	000 ó 255	0–100%
	3	Strobe	000 ó 009	No function
			010 ó 099	Strobe (slow to fast)
			100 ó 109	No function
			110 ó 179	Lighting effect
			180 ó 189	No function
		190 ó 255	Random strobe	
	4	Zoom	000 ó 255	0–100%
	5	Motor Reset	000 ó 200	No function
			201 ó 220	Motor reset
			221 ó 255	No function
DOS	Channel	Function	Value	Percent/Setting
	1	Dimmer	000 ó 255	0–100%
	2	Dimmer Fine	000 ó 255	0–100%
UNO	Channel	Function	Value	Percent/Setting
	1	Dimmer	000 ó 255	0–100%