

DMX CHART



www.chauvetprofessional.com

DMX Values

107 Ch

Channel	Function	Value	Percent/Setting
1	Pan	000 ⇄ 255	0-100%
2	Fine Pan	000 ⇄ 255	Fine control (16-bit)
3	Tilt	000 ⇄ 255	0-100%
4	Fine Tilt	000 ⇄ 255	Fine control (16-bit)
5	Pan/Tilt Speed	000 ⇄ 255	0-100%
6	Dimmer	000 ⇄ 255	0-100%
7	Fine Dimmer	000 ⇄ 255	Fine control (16-bit)
8	Shutter	000 ⇄ 019	off
		020 ⇄ 024	on
		025 ⇄ 064	strobe 1 with decreasing speed
		065 ⇄ 069	on
		070 ⇄ 084	strobe 2 (fast on slow off) with decreasing speed
		085 ⇄ 089	on
		090 ⇄ 104	strobe 3 (slow on fast off) with decreasing speed
		105 ⇄ 109	on
		110 ⇄ 124	strobe 4 (random strobe) with decreasing speed
		125 ⇄ 129	on
		130 ⇄ 144	strobe 5 (random fast on slow off) with decreasing speed
		145 ⇄ 149	on
		150 ⇄ 164	strobe 6 (random slow on fast off) with decreasing speed
		165 ⇄ 169	on
		170 ⇄ 184	strobe 7 (pulse strobe) with decreasing speed
		185 ⇄ 189	on
		190 ⇄ 204	strobe 8 (random pulse strobe) with decreasing speed
		205 ⇄ 209	on
9	CTC	000	No function
		001 ⇄ 255	2800 to 10,000K
		000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	R: 255 G: 0 B: + W: 0
10	Color	201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow

Channel	Function	Value	Percent/Setting
11	Gobo	000 ⇔ 003	No function
		004 ⇔ 006	Gobo 1
		007 ⇔ 009	Gobo 2
		010 ⇔ 012	Gobo 3
		013 ⇔ 015	Gobo 4
		016 ⇔ 018	Gobo 5
		019 ⇔ 021	Gobo 6
		022 ⇔ 024	Gobo 7
		025 ⇔ 027	Gobo 8
		028 ⇔ 030	Gobo 9
		031 ⇔ 033	No Gobo

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
11	Gobo	034 ⇌ 036	Gobo 10
		037 ⇌ 039	Gobo 11
		040 ⇌ 042	Gobo 12
		043 ⇌ 045	Gobo 13
		046 ⇌ 048	Gobo 14
		049 ⇌ 051	Gobo 15
		052 ⇌ 054	Gobo 16
		055 ⇌ 057	Gobo 17
		058 ⇌ 060	Gobo 18
		061 ⇌ 063	Gobo 19
		064 ⇌ 066	Gobo 20
		067 ⇌ 069	Gobo 21
		070 ⇌ 072	Gobo 22
		073 ⇌ 075	Gobo 23
		076 ⇌ 078	Gobo 24
		079 ⇌ 081	Gobo 25
		082 ⇌ 084	Gobo 26
		085 ⇌ 087	Gobo 27
		088 ⇌ 090	Gobo 28
		091 ⇌ 093	Gobo 29
		094 ⇌ 096	Gobo 30
		097 ⇌ 099	Gobo 31
		100 ⇌ 102	Gobo 32
		103 ⇌ 105	Gobo 33
		106 ⇌ 108	Gobo 34
		109 ⇌ 111	Gobo 35
		112 ⇌ 114	Gobo 36
		115 ⇌ 117	Gobo 37
		118 ⇌ 120	Gobo 38
		121 ⇌ 123	Gobo 39
		124 ⇌ 126	Gobo 40
		127 ⇌ 129	Gobo 41
		130 ⇌ 132	Gobo 42
		133 ⇌ 135	Gobo 43
		136 ⇌ 138	Gobo 44
		139 ⇌ 141	Gobo 45
		142 ⇌ 144	Gobo 46
		145 ⇌ 147	Gobo 47
		148 ⇌ 150	Gobo 48
		151 ⇌ 153	Gobo 49
		154 ⇌ 156	Gobo 50
		157 ⇌ 159	Gobo 51
		160 ⇌ 162	Gobo 52
		163 ⇌ 165	Gobo 53
		166 ⇌ 168	Gobo 54
		169 ⇌ 171	Gobo 55
		172 ⇌ 174	Gobo 56
		175 ⇌ 177	Gobo 57
		178 ⇌ 180	Gobo 58
		181 ⇌ 183	Gobo 59
		184 ⇌ 186	Gobo 60
		187 ⇌ 189	Gobo 61
		190 ⇌ 192	Gobo 62
		193 ⇌ 195	Gobo 63
		196 ⇌ 198	Gobo 64
		199 ⇌ 201	Gobo 65
		202 ⇌ 204	Gobo 66
		205 ⇌ 207	Gobo 67
		208 ⇌ 210	Gobo 68
		211 ⇌ 213	Gobo 69
		214 ⇌ 216	Gobo 70
		217 ⇌ 219	Gobo 71
		220 ⇌ 222	Gobo 72
		223 ⇌ 225	Gobo 73
		226 ⇌ 228	Gobo 74
		229 ⇌ 231	Gobo 75

Channel	Function	Value	Percent/Setting
11	Gobo	232 ⇄ 234	Gobo 76
		235 ⇄ 237	Gobo 77
		238 ⇄ 240	Gobo 78
		241 ⇄ 243	Gobo 79
		244 ⇄ 246	Gobo 80
		247 ⇄ 249	Gobo 81
		250 ⇄ 252	Gobo 82
		253 ⇄ 255	Gobo 83
12	LED Built-in	000 ⇄ 015	No function
		016 ⇄ 017	Built-in 1
		018 ⇄ 019	Built-in 2
		020 ⇄ 021	Built-in 3
		022 ⇄ 023	Built-in 4
		024 ⇄ 025	Built-in 5
		026 ⇄ 027	Built-in 6
		028 ⇄ 029	Built-in 7
		030 ⇄ 031	Built-in 8
		032 ⇄ 033	Built-in 9
		034 ⇄ 035	Built-in 10
		036 ⇄ 037	Built-in 11
		038 ⇄ 039	Built-in 12
		040 ⇄ 041	Built-in 13
		042 ⇄ 043	Built-in 14
		044 ⇄ 045	Built-in 15
		046 ⇄ 047	Built-in 16
		048 ⇄ 049	Built-in 17
		050 ⇄ 051	Built-in 18
		052 ⇄ 053	Built-in 19
		054 ⇄ 055	Built-in 20
		056 ⇄ 057	Built-in 21
		058 ⇄ 059	Built-in 22
		060 ⇄ 061	Built-in 23
		062 ⇄ 063	Built-in 24
		064 ⇄ 065	Built-in 25
		066 ⇄ 067	Built-in 26
		068 ⇄ 069	Built-in 27
		070 ⇄ 071	Built-in 28
		072 ⇄ 073	Built-in 29
		074 ⇄ 075	Built-in 30
		076 ⇄ 077	Built-in 31
		078 ⇄ 079	Built-in 32
		080 ⇄ 081	Built-in 33
		082 ⇄ 083	Built-in 34
		084 ⇄ 085	Built-in 35
		086 ⇄ 087	Built-in 36
		088 ⇄ 089	Built-in 37
		090 ⇄ 091	Built-in 38
		092 ⇄ 093	Built-in 39
		094 ⇄ 095	Built-in 40
		096 ⇄ 097	Built-in 41
		098 ⇄ 099	Built-in 42
		100 ⇄ 101	Built-in 43
		102 ⇄ 103	Built-in 44
		104 ⇄ 105	Built-in 45
		106 ⇄ 107	Built-in 46
		108 ⇄ 109	Built-in 47
		110 ⇄ 111	Built-in 48
		112 ⇄ 113	Built-in 49
		114 ⇄ 115	Built-in 50
		116 ⇄ 117	Built-in 51
		118 ⇄ 119	Built-in 52
		120 ⇄ 121	Built-in 53
		122 ⇄ 123	Built-in 54
		124 ⇄ 125	Built-in 55
		126 ⇄ 127	Built-in 56

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
12	LED Built-in	128 ⇄ 135	Built-in 57
		136 ⇄ 137	Built-in 58
		138 ⇄ 139	Built-in 59
		140 ⇄ 141	Built-in 60
		142 ⇄ 143	Built-in 61
		144 ⇄ 145	Built-in 62
		146 ⇄ 147	Built-in 63
		148 ⇄ 149	Built-in 64
		150 ⇄ 151	Built-in 65
		152 ⇄ 153	Built-in 66
		154 ⇄ 155	Built-in 67
		156 ⇄ 157	Built-in 68
		158 ⇄ 159	Built-in 69
		160 ⇄ 161	Built-in 70
		162 ⇄ 163	Built-in 71
		164 ⇄ 165	Built-in 72
		166 ⇄ 167	Built-in 73
		168 ⇄ 169	Built-in 74
		170 ⇄ 171	Built-in 75
		172 ⇄ 173	Built-in 76
		174 ⇄ 175	Built-in 77
		176 ⇄ 177	Built-in 78
		178 ⇄ 179	Built-in 79
		180 ⇄ 181	Built-in 80
		182 ⇄ 183	Built-in 81
		184 ⇄ 185	Built-in 82
		186 ⇄ 187	Built-in 83
		188 ⇄ 189	Built-in 84
		190 ⇄ 191	Built-in 85
		192 ⇄ 193	Built-in 86
		194 ⇄ 195	Built-in 87
		196 ⇄ 197	Built-in 88
		198 ⇄ 199	Built-in 89
		200 ⇄ 201	Built-in 90
		202 ⇄ 203	Built-in 91
		204 ⇄ 205	Built-in 92
		206 ⇄ 207	Built-in 93
		208 ⇄ 209	Built-in 94
		210 ⇄ 211	Built-in 95
		212 ⇄ 213	Built-in 96
		214 ⇄ 215	Built-in 97
		216 ⇄ 217	Built-in 98
		218 ⇄ 219	Built-in 99
		220 ⇄ 221	Built-in 100
		222 ⇄ 223	Built-in 101
		224 ⇄ 225	Built-in 102
		226 ⇄ 227	Built-in 103
		228 ⇄ 229	Built-in 104
		230 ⇄ 231	Built-in 105
		232 ⇄ 233	Built-in 106
		234 ⇄ 235	Built-in 107
		236 ⇄ 237	Built-in 108
		238 ⇄ 239	Built-in 109
		240 ⇄ 241	Built-in 110
		242 ⇄ 243	Built-in 111
		244 ⇄ 245	Built-in 112
		246 ⇄ 247	Built-in 113
		248 ⇄ 255	Built-in 114
13	LED Built-in Speed	000 ⇄ 127	Clockwise fast to slow
		128	Stop
		129 ⇄ 255	Counter-clockwise slow to fast
14	LED Built-in Delay	000 ⇄ 255	Fast to slow

Channel	Function	Value	Percent/Setting
15	Background Color Macros	000	No function
		001 ⇔ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇔ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇔ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇔ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇔ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇔ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇔ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇔ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇔ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇔ 200	R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇔ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇔ 247	Color change, fast to slow
		248 ⇔ 255	Color jump, fast to slow
16	Background Color Dimmer	000 ⇔ 255	0-100%
17	Background Color Fine Dimmer	000 ⇔ 255	Fine control (16-bit)
18	Background Red	000 ⇔ 255	0-100%
19	Background Fine Red	000 ⇔ 255	Fine control (16-bit)
20	Background Green	000 ⇔ 255	0-100%
21	Background Fine Green	000 ⇔ 255	Fine control (16-bit)
22	Background Blue	000 ⇔ 255	0-100%
23	Background Fine Blue	000 ⇔ 255	Fine control (16-bit)
24	Background White	000 ⇔ 255	0-100%
25	Background Fine White	000 ⇔ 255	Fine control (16-bit)
26	Zoom	000 ⇔ 255	0-100%

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
27	Control	000 ⇄ 009	No function
		010 ⇄ 014	Pan/Tilt blackout
		015 ⇄ 019	No function
		020 ⇄ 024	RGBW color mixing (5 sec.)
		025 ⇄ 029	CMY color mixing (5 sec.)
		030 ⇄ 034	No function
		035 ⇄ 039	No function
		040 ⇄ 044	No function
		045 ⇄ 049	No function
		050 ⇄ 054	Pan reset
		055 ⇄ 059	Tilt reset
		060 ⇄ 064	Zoom reset
		065 ⇄ 069	No function
		070 ⇄ 074	All reset
		075 ⇄ 079	No function
		080 ⇄ 084	Pan/Tilt reverse
		085 ⇄ 089	Pan reverse
		090 ⇄ 094	Tilt reverse
		095 ⇄ 099	Cancel pan reverse
		100 ⇄ 104	Cancel tilt reverse
		105 ⇄ 109	Cancel pan/tilt reverse
		110 ⇄ 114	No function
		115 ⇄ 119	No function
		120 ⇄ 124	Fan low speed
		125 ⇄ 129	Fan full speed
		130 ⇄ 134	Fan auto
		135 ⇄ 139	Dimmer Fast mode
		140 ⇄ 144	Dimmer Smooth mode
		145 ⇄ 255	No function
28	Red (Cyan)	000 ⇄ 255	0-100%
29	Fine Red (Cyan)	000 ⇄ 255	Fine control (16-bit)
30	Green (Magenta)	000 ⇄ 255	0-100%
31	Fine Green (Magenta)	000 ⇄ 255	Fine control (16-bit)
32	Blue (Yellow)	000 ⇄ 255	0-100%
33	Fine Blue (Yellow)	000 ⇄ 255	Fine control (16-bit)
34	White	000 ⇄ 255	0-100%
35	Fine White	000 ⇄ 255	Fine control (16-bit)
36	Red 1 (Cyan)	000 ⇄ 255	0-100%
37	Fine Red 1 (Cyan)	000 ⇄ 255	Fine control (16-bit)
38	Green 1 (Magenta)	000 ⇄ 255	0-100%
39	Fine Green 1 (Magenta)	000 ⇄ 255	Fine control (16-bit)
40	Blue 1 (Yellow)	000 ⇄ 255	0-100%
41	Fine Blue 1 (Yellow)	000 ⇄ 255	Fine control (16-bit)
42	White 1	000 ⇄ 255	0-100%
43	Fine White 1	000 ⇄ 255	Fine control (16-bit)
44	Red 2 (Cyan)	000 ⇄ 255	0-100%
45	Fine Red 2 (Cyan)	000 ⇄ 255	Fine control (16-bit)
46	Green 2 (Magenta)	000 ⇄ 255	0-100%
47	Fine Green 2 (Magenta)	000 ⇄ 255	Fine control (16-bit)
48	Blue 2 (Yellow)	000 ⇄ 255	0-100%
49	Fine Blue 2 (Yellow)	000 ⇄ 255	Fine control (16-bit)
50	White 2	000 ⇄ 255	0-100%
51	Fine White 2	000 ⇄ 255	Fine control (16-bit)
52	Red 3 (Cyan)	000 ⇄ 255	0-100%

Channel	Function	Value	Percent/Setting
53	Fine Red 3 (Cyan)	000 ⇄ 255	Fine control (16-bit)
54	Green 3 (Magenta)	000 ⇄ 255	0-100%
55	Fine Green 3 (Magenta)	000 ⇄ 255	Fine control (16-bit)
56	Blue 3 (Yellow)	000 ⇄ 255	0-100%
57	Fine Blue 3 (Yellow)	000 ⇄ 255	Fine control (16-bit)
58	White 3	000 ⇄ 255	0-100%
59	Fine White 3	000 ⇄ 255	Fine control (16-bit)
60	Red 4 (Cyan)	000 ⇄ 255	0-100%
61	Fine Red 4 (Cyan)	000 ⇄ 255	Fine control (16-bit)
62	Green 4 (Magenta)	000 ⇄ 255	0-100%
63	Fine Green 4 (Magenta)	000 ⇄ 255	Fine control (16-bit)
64	Blue 4 (Yellow)	000 ⇄ 255	0-100%
65	Fine Blue 4 (Yellow)	000 ⇄ 255	Fine control (16-bit)
66	White 4	000 ⇄ 255	0-100%
67	Fine White 4	000 ⇄ 255	Fine control (16-bit)
68	Red 5 (Cyan)	000 ⇄ 255	0-100%
69	Fine Red 5 (Cyan)	000 ⇄ 255	Fine control (16-bit)
70	Green 5 (Magenta)	000 ⇄ 255	0-100%
71	Fine Green 5 (Magenta)	000 ⇄ 255	Fine control (16-bit)
72	Blue 5 (Yellow)	000 ⇄ 255	0-100%
73	Fine Blue 5 (Yellow)	000 ⇄ 255	Fine control (16-bit)
74	White 5	000 ⇄ 255	0-100%
75	Fine White 5	000 ⇄ 255	Fine control (16-bit)
76	Red 6 (Cyan)	000 ⇄ 255	0-100%
77	Fine Red 6 (Cyan)	000 ⇄ 255	Fine control (16-bit)
78	Green 6 (Magenta)	000 ⇄ 255	0-100%
79	Fine Green 6 (Magenta)	000 ⇄ 255	Fine control (16-bit)
80	Blue 6 (Yellow)	000 ⇄ 255	0-100%
81	Fine Blue 6 (Yellow)	000 ⇄ 255	Fine control (16-bit)
82	White 6	000 ⇄ 255	0-100%
83	Fine White 6	000 ⇄ 255	Fine control (16-bit)
84	Red 7 (Cyan)	000 ⇄ 255	0-100%
85	Fine Red 7 (Cyan)	000 ⇄ 255	Fine control (16-bit)
86	Green 7 (Magenta)	000 ⇄ 255	0-100%
87	Fine Green 7 (Magenta)	000 ⇄ 255	Fine control (16-bit)
88	Blue 7 (Yellow)	000 ⇄ 255	0-100%
89	Fine Blue 7 (Yellow)	000 ⇄ 255	Fine control (16-bit)
90	White 7	000 ⇄ 255	0-100%
91	Fine White 7	000 ⇄ 255	Fine control (16-bit)
92	Red 8 (Cyan)	000 ⇄ 255	0-100%
93	Fine Red 8 (Cyan)	000 ⇄ 255	Fine control (16-bit)
94	Green 8 (Magenta)	000 ⇄ 255	0-100%

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
95	Fine Green 8 (Magenta)	000 ⇄ 255	Fine control (16-bit)
96	Blue 8 (Yellow)	000 ⇄ 255	0-100%
97	Fine Blue 8 (Yellow)	000 ⇄ 255	Fine control (16-bit)
98	White 8	000 ⇄ 255	0-100%
99	Fine White 8	000 ⇄ 255	Fine control (16-bit)
100	Red 9 (Cyan)	000 ⇄ 255	0-100%
101	Fine Red 9 (Cyan)	000 ⇄ 255	Fine control (16-bit)
102	Green 9 (Magenta)	000 ⇄ 255	0-100%
103	Fine Green 9 (Magenta)	000 ⇄ 255	Fine control (16-bit)
104	Blue 9 (Yellow)	000 ⇄ 255	0-100%
105	Fine Blue 9 (Yellow)	000 ⇄ 255	Fine control (16-bit)
106	White 9	000 ⇄ 255	0-100%
107	Fine White 9	000 ⇄ 255	Fine control (16-bit)

71 Ch

Channel	Function	Value	Percent/Setting
1	Pan	000 ⇄ 255	0-100%
2	Fine Pan	000 ⇄ 255	Fine control (16-bit)
3	Tilt	000 ⇄ 255	0-100%
4	Fine Tilt	000 ⇄ 255	Fine control (16-bit)
5	Pan/Tilt Speed	000 ⇄ 255	0-100%
6	Dimmer	000 ⇄ 255	0-100%
7	Fine Dimmer	000 ⇄ 255	Fine control (16-bit)
8	Shutter	000 ⇄ 019	off
		020 ⇄ 024	on
		025 ⇄ 064	strobe 1 with decreasing speed
		065 ⇄ 069	on
		070 ⇄ 084	strobe 2 (fast on slow off) with decreasing speed
		085 ⇄ 089	on
		090 ⇄ 104	strobe 3 (slow on fast off) with decreasing speed
		105 ⇄ 109	on
		110 ⇄ 124	strobe 4 (random strobe) with decreasing speed
		125 ⇄ 129	on
		130 ⇄ 144	strobe 5 (random fast on slow off) with decreasing speed
		145 ⇄ 149	on
		150 ⇄ 164	strobe 6 (random slow on fast off) with decreasing speed
		165 ⇄ 169	on
		170 ⇄ 184	strobe 7 (pulse strobe) with decreasing speed
		185 ⇄ 189	on
		190 ⇄ 204	strobe 8 (random pulse strobe) with decreasing speed
9	CTC	000	No function
		001 ⇄ 255	2800 to 10,000K

Channel	Function	Value	Percent/Setting
10	Color	000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow
11	Gobo	000 ⇄ 003	No function
		004 ⇄ 006	Gobo 1
		007 ⇄ 009	Gobo 2
		010 ⇄ 012	Gobo 3
		013 ⇄ 015	Gobo 4
		016 ⇄ 018	Gobo 5
		019 ⇄ 021	Gobo 6
		022 ⇄ 024	Gobo 7
		025 ⇄ 027	Gobo 8
		028 ⇄ 030	Gobo 9
		031 ⇄ 033	No Gobo
		034 ⇄ 036	Gobo 10
		037 ⇄ 039	Gobo 11
		040 ⇄ 042	Gobo 12
		043 ⇄ 045	Gobo 13
		046 ⇄ 048	Gobo 14
		049 ⇄ 051	Gobo 15
		052 ⇄ 054	Gobo 16
		055 ⇄ 057	Gobo 17
		058 ⇄ 060	Gobo 18
		061 ⇄ 063	Gobo 19
		064 ⇄ 066	Gobo 20
		067 ⇄ 069	Gobo 21
		070 ⇄ 072	Gobo 22
		073 ⇄ 075	Gobo 23
		076 ⇄ 078	Gobo 24
		079 ⇄ 081	Gobo 25
		082 ⇄ 084	Gobo 26
		085 ⇄ 087	Gobo 27
		088 ⇄ 090	Gobo 28
		091 ⇄ 093	Gobo 29
		094 ⇄ 096	Gobo 30
		097 ⇄ 099	Gobo 31
		100 ⇄ 102	Gobo 32
		103 ⇄ 105	Gobo 33
		106 ⇄ 108	Gobo 34
		109 ⇄ 111	Gobo 35
		112 ⇄ 114	Gobo 36
		115 ⇄ 117	Gobo 37
		118 ⇄ 120	Gobo 38
		121 ⇄ 123	Gobo 39

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
11	Gobo	124 ⇄ 126	Gobo 40
		127 ⇄ 129	Gobo 41
		130 ⇄ 132	Gobo 42
		133 ⇄ 135	Gobo 43
		136 ⇄ 138	Gobo 44
		139 ⇄ 141	Gobo 45
		142 ⇄ 144	Gobo 46
		145 ⇄ 147	Gobo 47
		148 ⇄ 150	Gobo 48
		151 ⇄ 153	Gobo 49
		154 ⇄ 156	Gobo 50
		157 ⇄ 159	Gobo 51
		160 ⇄ 162	Gobo 52
		163 ⇄ 165	Gobo 53
		166 ⇄ 168	Gobo 54
		169 ⇄ 171	Gobo 55
		172 ⇄ 174	Gobo 56
		175 ⇄ 177	Gobo 57
		178 ⇄ 180	Gobo 58
		181 ⇄ 183	Gobo 59
		184 ⇄ 186	Gobo 60
		187 ⇄ 189	Gobo 61
		190 ⇄ 192	Gobo 62
		193 ⇄ 195	Gobo 63
		196 ⇄ 198	Gobo 64
		199 ⇄ 201	Gobo 65
		202 ⇄ 204	Gobo 66
		205 ⇄ 207	Gobo 67
		208 ⇄ 210	Gobo 68
		211 ⇄ 213	Gobo 69
		214 ⇄ 216	Gobo 70
		217 ⇄ 219	Gobo 71
		220 ⇄ 222	Gobo 72
		223 ⇄ 225	Gobo 73
		226 ⇄ 228	Gobo 74
		229 ⇄ 231	Gobo 75
		232 ⇄ 234	Gobo 76
		235 ⇄ 237	Gobo 77
		238 ⇄ 240	Gobo 78
		241 ⇄ 243	Gobo 79
		244 ⇄ 246	Gobo 80
		247 ⇄ 249	Gobo 81
		250 ⇄ 252	Gobo 82
		253 ⇄ 255	Gobo 83
12	LED Built-in	000 ⇄ 015	No function
		016 ⇄ 017	Built-in 1
		018 ⇄ 019	Built-in 2
		020 ⇄ 021	Built-in 3
		022 ⇄ 023	Built-in 4
		024 ⇄ 025	Built-in 5
		026 ⇄ 027	Built-in 6
		028 ⇄ 029	Built-in 7
		030 ⇄ 031	Built-in 8
		032 ⇄ 033	Built-in 9
		034 ⇄ 035	Built-in 10
		036 ⇄ 037	Built-in 11
		038 ⇄ 039	Built-in 12
		040 ⇄ 041	Built-in 13
		042 ⇄ 043	Built-in 14
		044 ⇄ 045	Built-in 15
		046 ⇄ 047	Built-in 16
		048 ⇄ 049	Built-in 17
		050 ⇄ 051	Built-in 18
		052 ⇄ 053	Built-in 19
		054 ⇄ 055	Built-in 20

Channel	Function	Value	Percent/Setting
12	LED Built-in	056 ⇄ 057	Built-in 21
		058 ⇄ 059	Built-in 22
		060 ⇄ 061	Built-in 23
		062 ⇄ 063	Built-in 24
		064 ⇄ 065	Built-in 25
		066 ⇄ 067	Built-in 26
		068 ⇄ 069	Built-in 27
		070 ⇄ 071	Built-in 28
		072 ⇄ 073	Built-in 29
		074 ⇄ 075	Built-in 30
		076 ⇄ 077	Built-in 31
		078 ⇄ 079	Built-in 32
		080 ⇄ 081	Built-in 33
		082 ⇄ 083	Built-in 34
		084 ⇄ 085	Built-in 35
		086 ⇄ 087	Built-in 36
		088 ⇄ 089	Built-in 37
		090 ⇄ 091	Built-in 38
		092 ⇄ 093	Built-in 39
		094 ⇄ 095	Built-in 40
		096 ⇄ 097	Built-in 41
		098 ⇄ 099	Built-in 42
		100 ⇄ 101	Built-in 43
		102 ⇄ 103	Built-in 44
		104 ⇄ 105	Built-in 45
		106 ⇄ 107	Built-in 46
		108 ⇄ 109	Built-in 47
		110 ⇄ 111	Built-in 48
		112 ⇄ 113	Built-in 49
		114 ⇄ 115	Built-in 50
		116 ⇄ 117	Built-in 51
		118 ⇄ 119	Built-in 52
		120 ⇄ 121	Built-in 53
		122 ⇄ 123	Built-in 54
		124 ⇄ 125	Built-in 55
		126 ⇄ 127	Built-in 56
		128 ⇄ 135	Built-in 57
		136 ⇄ 137	Built-in 58
		138 ⇄ 139	Built-in 59
		140 ⇄ 141	Built-in 60
		142 ⇄ 143	Built-in 61
		144 ⇄ 145	Built-in 62
		146 ⇄ 147	Built-in 63
		148 ⇄ 149	Built-in 64
		150 ⇄ 151	Built-in 65
		152 ⇄ 153	Built-in 66
		154 ⇄ 155	Built-in 67
		156 ⇄ 157	Built-in 68
		158 ⇄ 159	Built-in 69
		160 ⇄ 161	Built-in 70
		162 ⇄ 163	Built-in 71
		164 ⇄ 165	Built-in 72
		166 ⇄ 167	Built-in 73
		168 ⇄ 169	Built-in 74
		170 ⇄ 171	Built-in 75
		172 ⇄ 173	Built-in 76
		174 ⇄ 175	Built-in 77
		176 ⇄ 177	Built-in 78
		178 ⇄ 179	Built-in 79
		180 ⇄ 181	Built-in 80
		182 ⇄ 183	Built-in 81
		184 ⇄ 185	Built-in 82
		186 ⇄ 187	Built-in 83

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
12	LED Built-in	188 ⇄ 189	Built-in 84
		190 ⇄ 191	Built-in 85
		192 ⇄ 193	Built-in 86
		194 ⇄ 195	Built-in 87
		196 ⇄ 197	Built-in 88
		198 ⇄ 199	Built-in 89
		200 ⇄ 201	Built-in 90
		202 ⇄ 203	Built-in 91
		204 ⇄ 205	Built-in 92
		206 ⇄ 207	Built-in 93
		208 ⇄ 209	Built-in 94
		210 ⇄ 211	Built-in 95
		212 ⇄ 213	Built-in 96
		214 ⇄ 215	Built-in 97
		216 ⇄ 217	Built-in 98
		218 ⇄ 219	Built-in 99
		220 ⇄ 221	Built-in 100
		222 ⇄ 223	Built-in 101
		224 ⇄ 225	Built-in 102
		226 ⇄ 227	Built-in 103
		228 ⇄ 229	Built-in 104
		230 ⇄ 231	Built-in 105
		232 ⇄ 233	Built-in 106
		234 ⇄ 235	Built-in 107
		236 ⇄ 237	Built-in 108
		238 ⇄ 239	Built-in 109
		240 ⇄ 241	Built-in 110
		242 ⇄ 243	Built-in 111
		244 ⇄ 245	Built-in 112
		246 ⇄ 247	Built-in 113
		248 ⇄ 255	Built-in 114
13	LED Built-in Speed	000 ⇄ 127	Clockwise fast to slow
		128	Stop
		129 ⇄ 255	Counter-clockwise slow to fast
14	LED Built-in Delay	000 ⇄ 255	Fast to slow
15	Background Color Macros	000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	Blue R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	Cyan R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	Green R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	Yellow R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	Red R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	Magenta R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow
16	Background Color Dimmer	000 ⇄ 255	0-100%
17	Background Red	000 ⇄ 255	0-100%
18	Background Green	000 ⇄ 255	0-100%
19	Background Blue	000 ⇄ 255	0-100%

Channel	Function	Value	Percent/Setting
20	Background White	000 ⇄ 255	0-100%
21	Zoom	000 ⇄ 255	0-100%
22	Control	000 ⇄ 009	No function
		010 ⇄ 014	Pan/Tilt blackout
		015 ⇄ 019	No function
		020 ⇄ 024	RGBW color mixing (5 sec.)
		025 ⇄ 029	CMY color mixing (5 sec.)
		030 ⇄ 034	No function
		035 ⇄ 039	No function
		040 ⇄ 044	No function
		045 ⇄ 049	No function
		050 ⇄ 054	Pan reset
		055 ⇄ 059	Tilt reset
		060 ⇄ 064	Zoom reset
		065 ⇄ 069	No function
		070 ⇄ 074	All reset
		075 ⇄ 079	No function
		080 ⇄ 084	Pan/Tilt reverse
		085 ⇄ 089	Pan reverse
		090 ⇄ 094	Tilt reverse
		095 ⇄ 099	Cancel pan reverse
		100 ⇄ 104	Cancel tilt reverse
		105 ⇄ 109	Cancel pan/tilt reverse
		110 ⇄ 114	No function
		115 ⇄ 119	No function
		120 ⇄ 124	Fan low speed
		125 ⇄ 129	Fan full speed
		130 ⇄ 134	Fan auto
		135 ⇄ 139	Dimmer Fast mode
		140 ⇄ 144	Dimmer Smooth mode
		145 ⇄ 255	No function
23	Red (Cyan)	000 ⇄ 255	0-100%
24	Green (Magenta)	000 ⇄ 255	0-100%
25	Blue (Yellow)	000 ⇄ 255	0-100%
26	White	000 ⇄ 255	0-100%
27	Dimmer 1	000 ⇄ 255	0-100%
28	Red 1 (Cyan)	000 ⇄ 255	0-100%
29	Green 1 (Magenta)	000 ⇄ 255	0-100%
30	Blue 1 (Yellow)	000 ⇄ 255	0-100%
31	White 1	000 ⇄ 255	0-100%
32	Dimmer 2	000 ⇄ 255	0-100%
33	Red 2 (Cyan)	000 ⇄ 255	0-100%
34	Green 2 (Magenta)	000 ⇄ 255	0-100%
35	Blue 2 (Yellow)	000 ⇄ 255	0-100%
36	White 2	000 ⇄ 255	0-100%
37	Dimmer 3	000 ⇄ 255	0-100%
38	Red 3 (Cyan)	000 ⇄ 255	0-100%
39	Green 3 (Magenta)	000 ⇄ 255	0-100%
40	Blue 3 (Yellow)	000 ⇄ 255	0-100%
41	White 3	000 ⇄ 255	0-100%
42	Dimmer 4	000 ⇄ 255	0-100%
43	Red 4 (Cyan)	000 ⇄ 255	0-100%
44	Green 4 (Magenta)	000 ⇄ 255	0-100%
45	Blue 4 (Yellow)	000 ⇄ 255	0-100%
46	White 4	000 ⇄ 255	0-100%
47	Dimmer 5	000 ⇄ 255	0-100%

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
48	Red 5 (Cyan)	000 ⇄ 255	0-100%
49	Green 5 (Magenta)	000 ⇄ 255	0-100%
50	Blue 5 (Yellow)	000 ⇄ 255	0-100%
51	White 5	000 ⇄ 255	0-100%
52	Dimmer 6	000 ⇄ 255	0-100%
53	Red 6 (Cyan)	000 ⇄ 255	0-100%
54	Green 6 (Magenta)	000 ⇄ 255	0-100%
55	Blue 6 (Yellow)	000 ⇄ 255	0-100%
56	White 6	000 ⇄ 255	0-100%
57	Dimmer 7	000 ⇄ 255	0-100%
58	Red 7 (Cyan)	000 ⇄ 255	0-100%
59	Green 7 (Magenta)	000 ⇄ 255	0-100%
60	Blue 7 (Yellow)	000 ⇄ 255	0-100%
61	White 7	000 ⇄ 255	0-100%
62	Dimmer 8	000 ⇄ 255	0-100%
63	Red 8 (Cyan)	000 ⇄ 255	0-100%
64	Green 8 (Magenta)	000 ⇄ 255	0-100%
65	Blue 8 (Yellow)	000 ⇄ 255	0-100%
66	White 8	000 ⇄ 255	0-100%
67	Dimmer 9	000 ⇄ 255	0-100%
68	Red 9 (Cyan)	000 ⇄ 255	0-100%
69	Green 9 (Magenta)	000 ⇄ 255	0-100%
70	Blue 9 (Yellow)	000 ⇄ 255	0-100%
71	White 9	000 ⇄ 255	0-100%

62 Ch

Channel	Function	Value	Percent/Setting
1	Pan	000 ⇄ 255	0-100%
2	Fine Pan	000 ⇄ 255	Fine control (16-bit)
3	Tilt	000 ⇄ 255	0-100%
4	Fine Tilt	000 ⇄ 255	Fine control (16-bit)
5	Pan/Tilt Speed	000 ⇄ 255	0-100%
6	Dimmer	000 ⇄ 255	0-100%
7	Fine Dimmer	000 ⇄ 255	Fine control (16-bit)

Channel	Function	Value	Percent/Setting
8	Shutter	000 ⇄ 019	off
		020 ⇄ 024	on
		025 ⇄ 064	strobe 1 with decreasing speed
		065 ⇄ 069	on
		070 ⇄ 084	strobe 2 (fast on slow off) with decreasing speed
		085 ⇄ 089	on
		090 ⇄ 104	strobe 3 (slow on fast off) with decreasing speed
		105 ⇄ 109	on
		110 ⇄ 124	strobe 4 (random strobe) with decreasing speed
		125 ⇄ 129	on
		130 ⇄ 144	strobe 5 (random fast on slow off) with decreasing speed
		145 ⇄ 149	on
		150 ⇄ 164	strobe 6 (random slow on fast off) with decreasing speed
		165 ⇄ 169	on
		170 ⇄ 184	strobe 7 (pulse strobe) with decreasing speed
		185 ⇄ 189	on
		190 ⇄ 204	strobe 8 (random pulse strobe) with decreasing speed
		205 ⇄ 209	on
		210 ⇄ 224	strobe 9 (fade on or off) with decreasing speed
		225 ⇄ 229	on
		230 ⇄ 244	strobe 10 (pulse strobe) with decreasing speed
		245 ⇄ 255	on
9	CTC	000	No function
		001 ⇄ 255	2800 to 10,000K
10	Color	000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
11	Gobo	000 ⇄ 003	No function
		004 ⇄ 006	Gobo 1
		007 ⇄ 009	Gobo 2
		010 ⇄ 012	Gobo 3
		013 ⇄ 015	Gobo 4
		016 ⇄ 018	Gobo 5
		019 ⇄ 021	Gobo 6
		022 ⇄ 024	Gobo 7
		025 ⇄ 027	Gobo 8
		028 ⇄ 030	Gobo 9
		031 ⇄ 033	No Gobo
		034 ⇄ 036	Gobo 10
		037 ⇄ 039	Gobo 11
		040 ⇄ 042	Gobo 12
		043 ⇄ 045	Gobo 13
		046 ⇄ 048	Gobo 14
		049 ⇄ 051	Gobo 15
		052 ⇄ 054	Gobo 16
		055 ⇄ 057	Gobo 17
		058 ⇄ 060	Gobo 18
		061 ⇄ 063	Gobo 19
		064 ⇄ 066	Gobo 20
		067 ⇄ 069	Gobo 21
		070 ⇄ 072	Gobo 22
		073 ⇄ 075	Gobo 23
		076 ⇄ 078	Gobo 24
		079 ⇄ 081	Gobo 25
		082 ⇄ 084	Gobo 26
		085 ⇄ 087	Gobo 27
		088 ⇄ 090	Gobo 28
		091 ⇄ 093	Gobo 29
		094 ⇄ 096	Gobo 30
		097 ⇄ 099	Gobo 31
		100 ⇄ 102	Gobo 32
		103 ⇄ 105	Gobo 33
		106 ⇄ 108	Gobo 34
		109 ⇄ 111	Gobo 35
		112 ⇄ 114	Gobo 36
		115 ⇄ 117	Gobo 37
		118 ⇄ 120	Gobo 38
		121 ⇄ 123	Gobo 39

Channel	Function	Value	Percent/Setting
11	Gobo	124 ⇄ 126	Gobo 40
		127 ⇄ 129	Gobo 41
		130 ⇄ 132	Gobo 42
		133 ⇄ 135	Gobo 43
		136 ⇄ 138	Gobo 44
		139 ⇄ 141	Gobo 45
		142 ⇄ 144	Gobo 46
		145 ⇄ 147	Gobo 47
		148 ⇄ 150	Gobo 48
		151 ⇄ 153	Gobo 49
		154 ⇄ 156	Gobo 50
		157 ⇄ 159	Gobo 51
		160 ⇄ 162	Gobo 52
		163 ⇄ 165	Gobo 53
		166 ⇄ 168	Gobo 54
		169 ⇄ 171	Gobo 55
		172 ⇄ 174	Gobo 56
		175 ⇄ 177	Gobo 57
		178 ⇄ 180	Gobo 58
		181 ⇄ 183	Gobo 59
		184 ⇄ 186	Gobo 60
		187 ⇄ 189	Gobo 61
		190 ⇄ 192	Gobo 62
		193 ⇄ 195	Gobo 63
		196 ⇄ 198	Gobo 64
		199 ⇄ 201	Gobo 65
		202 ⇄ 204	Gobo 66
		205 ⇄ 207	Gobo 67
		208 ⇄ 210	Gobo 68
		211 ⇄ 213	Gobo 69
		214 ⇄ 216	Gobo 70
		217 ⇄ 219	Gobo 71
		220 ⇄ 222	Gobo 72
		223 ⇄ 225	Gobo 73
		226 ⇄ 228	Gobo 74
		229 ⇄ 231	Gobo 75
		232 ⇄ 234	Gobo 76
		235 ⇄ 237	Gobo 77
		238 ⇄ 240	Gobo 78
		241 ⇄ 243	Gobo 79
		244 ⇄ 246	Gobo 80
		247 ⇄ 249	Gobo 81
		250 ⇄ 252	Gobo 82
		253 ⇄ 255	Gobo 83
12	LED Built-in	000 ⇄ 015	No function
		016 ⇄ 017	Built-in 1
		018 ⇄ 019	Built-in 2
		020 ⇄ 021	Built-in 3
		022 ⇄ 023	Built-in 4
		024 ⇄ 025	Built-in 5
		026 ⇄ 027	Built-in 6
		028 ⇄ 029	Built-in 7
		030 ⇄ 031	Built-in 8
		032 ⇄ 033	Built-in 9
		034 ⇄ 035	Built-in 10
		036 ⇄ 037	Built-in 11
		038 ⇄ 039	Built-in 12
		040 ⇄ 041	Built-in 13
		042 ⇄ 043	Built-in 14
		044 ⇄ 045	Built-in 15
		046 ⇄ 047	Built-in 16
		048 ⇄ 049	Built-in 17
		050 ⇄ 051	Built-in 18
		052 ⇄ 053	Built-in 19
		054 ⇄ 055	Built-in 20

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
12	LED Built-in	056 ⇄ 057	Built-in 21
		058 ⇄ 059	Built-in 22
		060 ⇄ 061	Built-in 23
		062 ⇄ 063	Built-in 24
		064 ⇄ 065	Built-in 25
		066 ⇄ 067	Built-in 26
		068 ⇄ 069	Built-in 27
		070 ⇄ 071	Built-in 28
		072 ⇄ 073	Built-in 29
		074 ⇄ 075	Built-in 30
		076 ⇄ 077	Built-in 31
		078 ⇄ 079	Built-in 32
		080 ⇄ 081	Built-in 33
		082 ⇄ 083	Built-in 34
		084 ⇄ 085	Built-in 35
		086 ⇄ 087	Built-in 36
		088 ⇄ 089	Built-in 37
		090 ⇄ 091	Built-in 38
		092 ⇄ 093	Built-in 39
		094 ⇄ 095	Built-in 40
		096 ⇄ 097	Built-in 41
		098 ⇄ 099	Built-in 42
		100 ⇄ 101	Built-in 43
		102 ⇄ 103	Built-in 44
		104 ⇄ 105	Built-in 45
		106 ⇄ 107	Built-in 46
		108 ⇄ 109	Built-in 47
		110 ⇄ 111	Built-in 48
		112 ⇄ 113	Built-in 49
		114 ⇄ 115	Built-in 50
		116 ⇄ 117	Built-in 51
		118 ⇄ 119	Built-in 52
		120 ⇄ 121	Built-in 53
		122 ⇄ 123	Built-in 54
		124 ⇄ 125	Built-in 55
		126 ⇄ 127	Built-in 56
		128 ⇄ 135	Built-in 57
		136 ⇄ 137	Built-in 58
		138 ⇄ 139	Built-in 59
		140 ⇄ 141	Built-in 60
		142 ⇄ 143	Built-in 61
		144 ⇄ 145	Built-in 62
		146 ⇄ 147	Built-in 63
		148 ⇄ 149	Built-in 64
		150 ⇄ 151	Built-in 65
		152 ⇄ 153	Built-in 66
		154 ⇄ 155	Built-in 67
		156 ⇄ 157	Built-in 68
		158 ⇄ 159	Built-in 69
		160 ⇄ 161	Built-in 70
		162 ⇄ 163	Built-in 71
		164 ⇄ 165	Built-in 72
		166 ⇄ 167	Built-in 73
		168 ⇄ 169	Built-in 74
		170 ⇄ 171	Built-in 75
		172 ⇄ 173	Built-in 76
		174 ⇄ 175	Built-in 77
		176 ⇄ 177	Built-in 78
		178 ⇄ 179	Built-in 79
		180 ⇄ 181	Built-in 80
		182 ⇄ 183	Built-in 81
		184 ⇄ 185	Built-in 82
		186 ⇄ 187	Built-in 83
		188 ⇄ 189	Built-in 84
		190 ⇄ 191	Built-in 85

Channel	Function	Value	Percent/Setting
12	LED Built-in	192 ⇄ 193	Built-in 86
		194 ⇄ 195	Built-in 87
		196 ⇄ 197	Built-in 88
		198 ⇄ 199	Built-in 89
		200 ⇄ 201	Built-in 90
		202 ⇄ 203	Built-in 91
		204 ⇄ 205	Built-in 92
		206 ⇄ 207	Built-in 93
		208 ⇄ 209	Built-in 94
		210 ⇄ 211	Built-in 95
		212 ⇄ 213	Built-in 96
		214 ⇄ 215	Built-in 97
		216 ⇄ 217	Built-in 98
		218 ⇄ 219	Built-in 99
		220 ⇄ 221	Built-in 100
		222 ⇄ 223	Built-in 101
		224 ⇄ 225	Built-in 102
		226 ⇄ 227	Built-in 103
		228 ⇄ 229	Built-in 104
		230 ⇄ 231	Built-in 105
		232 ⇄ 233	Built-in 106
		234 ⇄ 235	Built-in 107
		236 ⇄ 237	Built-in 108
		238 ⇄ 239	Built-in 109
		240 ⇄ 241	Built-in 110
		242 ⇄ 243	Built-in 111
		244 ⇄ 245	Built-in 112
		246 ⇄ 247	Built-in 113
		248 ⇄ 255	Built-in 114
13	LED Built-in Speed	000 ⇄ 127	Clockwise fast to slow
		128	Stop
		129 ⇄ 255	Counter-clockwise slow to fast
14	LED Built-in Delay	000 ⇄ 255	Fast to slow
15	Background Color Macros	000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow
16	Background Color Dimmer	000 ⇄ 255	0-100%
17	Background Red	000 ⇄ 255	0-100%
18	Background Green	000 ⇄ 255	0-100%
19	Background Blue	000 ⇄ 255	0-100%
20	Background White	000 ⇄ 255	0-100%
21	Zoom	000 ⇄ 255	0-100%

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
22	Control	001 ⇄ 009	No function
		010 ⇄ 014	Pan/Tilt blackout
		015 ⇄ 019	No function
		020 ⇄ 024	RGBW color mixing (5 sec.)
		025 ⇄ 029	CMY color mixing (5 sec.)
		030 ⇄ 034	No function
		035 ⇄ 039	No function
		040 ⇄ 044	No function
		045 ⇄ 049	No function
		050 ⇄ 054	Pan reset
		055 ⇄ 059	Tilt reset
		060 ⇄ 064	Zoom reset
		065 ⇄ 069	No function
		070 ⇄ 074	All reset
		075 ⇄ 079	No function
		080 ⇄ 084	Pan/Tilt reverse
		085 ⇄ 089	Pan reverse
		090 ⇄ 094	Tilt reverse
		095 ⇄ 099	Cancel pan reverse
		100 ⇄ 104	Cancel tilt reverse
		105 ⇄ 109	Cancel pan/tilt reverse
		110 ⇄ 114	No function
		115 ⇄ 119	No function
		120 ⇄ 124	Fan low speed
		125 ⇄ 129	Fan full speed
		130 ⇄ 134	Fan auto
		135 ⇄ 139	Dimmer Fast mode
		140 ⇄ 144	Dimmer Smooth mode
		145 ⇄ 255	No function
23	Red (Cyan)	000 ⇄ 255	0-100%
24	Green (Magenta)	000 ⇄ 255	0-100%
25	Blue (Yellow)	000 ⇄ 255	0-100%
26	White	000 ⇄ 255	0-100%
27	Red 1 (Cyan)	000 ⇄ 255	0-100%
28	Green 1 (Magenta)	000 ⇄ 255	0-100%
29	Blue 1 (Yellow)	000 ⇄ 255	0-100%
30	White 1	000 ⇄ 255	0-100%
31	Red 2 (Cyan)	000 ⇄ 255	0-100%
32	Green 2 (Magenta)	000 ⇄ 255	0-100%
33	Blue 2 (Yellow)	000 ⇄ 255	0-100%
34	White 2	000 ⇄ 255	0-100%
35	Red 3 (Cyan)	000 ⇄ 255	0-100%
36	Green 3 (Magenta)	000 ⇄ 255	0-100%
37	Blue 3 (Yellow)	000 ⇄ 255	0-100%
38	White 3	000 ⇄ 255	0-100%
39	Red 4 (Cyan)	000 ⇄ 255	0-100%
40	Green 4 (Magenta)	000 ⇄ 255	0-100%
41	Blue 4 (Yellow)	000 ⇄ 255	0-100%
42	White 4	000 ⇄ 255	0-100%
43	Red 5 (Cyan)	000 ⇄ 255	0-100%
44	Green 5 (Magenta)	000 ⇄ 255	0-100%
45	Blue 5 (Yellow)	000 ⇄ 255	0-100%
46	White 5	000 ⇄ 255	0-100%
47	Red 6 (Cyan)	000 ⇄ 255	0-100%
48	Green 6 (Magenta)	000 ⇄ 255	0-100%

Channel	Function	Value	Percent/Setting
49	Blue 6 (Yellow)	000 ⇄ 255	0-100%
50	White 6	000 ⇄ 255	0-100%
51	Red 7 (Cyan)	000 ⇄ 255	0-100%
52	Green 7 (Magenta)	000 ⇄ 255	0-100%
53	Blue 7 (Yellow)	000 ⇄ 255	0-100%
54	White 7	000 ⇄ 255	0-100%
55	Red 8 (Cyan)	000 ⇄ 255	0-100%
56	Green 8 (Magenta)	000 ⇄ 255	0-100%
57	Blue 8 (Yellow)	000 ⇄ 255	0-100%
58	White 8	000 ⇄ 255	0-100%
59	Red 9 (Cyan)	000 ⇄ 255	0-100%
60	Green 9 (Magenta)	000 ⇄ 255	0-100%
61	Blue 9 (Yellow)	000 ⇄ 255	0-100%
62	White 9	000 ⇄ 255	0-100%

21 Ch

Channel	Function	Value	Percent/Setting
1	Pan	000 ⇄ 255	0-100%
2	Fine Pan	000 ⇄ 255	Fine control (16-bit)
3	Tilt	000 ⇄ 255	0-100%
4	Fine Tilt	000 ⇄ 255	Fine control (16-bit)
5	Pan/Tilt Speed	000 ⇄ 255	0-100%
6	Dimmer	000 ⇄ 255	0-100%
7	Shutter	000 ⇄ 019	off
		020 ⇄ 024	on
		025 ⇄ 064	strobe 1 with decreasing speed
		065 ⇄ 069	on
		070 ⇄ 084	strobe 2 (fast on slow off) with decreasing speed
		085 ⇄ 089	on
		090 ⇄ 104	strobe 3 (slow on fast off) with decreasing speed
		105 ⇄ 109	on
		110 ⇄ 124	strobe 4 (random strobe) with decreasing speed
		125 ⇄ 129	on
		130 ⇄ 144	strobe 5 (random fast on slow off) with decreasing speed
		145 ⇄ 149	on
		150 ⇄ 164	strobe 6 (random slow on fast off) with decreasing speed
		165 ⇄ 169	on
		170 ⇄ 184	strobe 7 (pulse strobe) with decreasing speed
		185 ⇄ 189	on
		190 ⇄ 204	strobe 8 (random pulse strobe) with decreasing speed
		205 ⇄ 209	on
		210 ⇄ 224	strobe 9 (fade on or off) with decreasing speed
		225 ⇄ 229	on
		230 ⇄ 244	strobe 10 (pulse strobe) with decreasing speed
		245 ⇄ 255	on
8	CTC	000	No function
		001 ⇄ 255	2800 to 10,000K

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
9	Color	000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow
10	Gobo	000 ⇄ 003	No function
		004 ⇄ 006	Gobo 1
		007 ⇄ 009	Gobo 2
		010 ⇄ 012	Gobo 3
		013 ⇄ 015	Gobo 4
		016 ⇄ 018	Gobo 5
		019 ⇄ 021	Gobo 6
		022 ⇄ 024	Gobo 7
		025 ⇄ 027	Gobo 8
		028 ⇄ 030	Gobo 9
		031 ⇄ 033	No Gobo
		034 ⇄ 036	Gobo 10
		037 ⇄ 039	Gobo 11
		040 ⇄ 042	Gobo 12
		043 ⇄ 045	Gobo 13
		046 ⇄ 048	Gobo 14
		049 ⇄ 051	Gobo 15
		052 ⇄ 054	Gobo 16
		055 ⇄ 057	Gobo 17
		058 ⇄ 060	Gobo 18
		061 ⇄ 063	Gobo 19
		064 ⇄ 066	Gobo 20
		067 ⇄ 069	Gobo 21
		070 ⇄ 072	Gobo 22
		073 ⇄ 075	Gobo 23
		076 ⇄ 078	Gobo 24
		079 ⇄ 081	Gobo 25
		082 ⇄ 084	Gobo 26
		085 ⇄ 087	Gobo 27
		088 ⇄ 090	Gobo 28
		091 ⇄ 093	Gobo 29
		094 ⇄ 096	Gobo 30
		097 ⇄ 099	Gobo 31
		100 ⇄ 102	Gobo 32
		103 ⇄ 105	Gobo 33
		106 ⇄ 108	Gobo 34
		109 ⇄ 111	Gobo 35
		112 ⇄ 114	Gobo 36
		115 ⇄ 117	Gobo 37
		118 ⇄ 120	Gobo 38
		121 ⇄ 123	Gobo 39

Channel	Function	Value	Percent/Setting
10	Gobo	124 ⇄ 126	Gobo 40
		127 ⇄ 129	Gobo 41
		130 ⇄ 132	Gobo 42
		133 ⇄ 135	Gobo 43
		136 ⇄ 138	Gobo 44
		139 ⇄ 141	Gobo 45
		142 ⇄ 144	Gobo 46
		145 ⇄ 147	Gobo 47
		148 ⇄ 150	Gobo 48
		151 ⇄ 153	Gobo 49
		154 ⇄ 156	Gobo 50
		157 ⇄ 159	Gobo 51
		160 ⇄ 162	Gobo 52
		163 ⇄ 165	Gobo 53
		166 ⇄ 168	Gobo 54
		169 ⇄ 171	Gobo 55
		172 ⇄ 174	Gobo 56
		175 ⇄ 177	Gobo 57
		178 ⇄ 180	Gobo 58
		181 ⇄ 183	Gobo 59
		184 ⇄ 186	Gobo 60
		187 ⇄ 189	Gobo 61
		190 ⇄ 192	Gobo 62
		193 ⇄ 195	Gobo 63
		196 ⇄ 198	Gobo 64
		199 ⇄ 201	Gobo 65
		202 ⇄ 204	Gobo 66
		205 ⇄ 207	Gobo 67
		208 ⇄ 210	Gobo 68
		211 ⇄ 213	Gobo 69
		214 ⇄ 216	Gobo 70
		217 ⇄ 219	Gobo 71
		220 ⇄ 222	Gobo 72
		223 ⇄ 225	Gobo 73
		226 ⇄ 228	Gobo 74
		229 ⇄ 231	Gobo 75
		232 ⇄ 234	Gobo 76
		235 ⇄ 237	Gobo 77
		238 ⇄ 240	Gobo 78
		241 ⇄ 243	Gobo 79
		244 ⇄ 246	Gobo 80
		247 ⇄ 249	Gobo 81
		250 ⇄ 252	Gobo 82
		253 ⇄ 255	Gobo 83
11	LED Built-in	001 ⇄ 015	No function
		016 ⇄ 017	Built-in 1
		018 ⇄ 019	Built-in 2
		020 ⇄ 021	Built-in 3
		022 ⇄ 023	Built-in 4
		024 ⇄ 025	Built-in 5
		026 ⇄ 027	Built-in 6
		028 ⇄ 029	Built-in 7
		030 ⇄ 031	Built-in 8
		032 ⇄ 033	Built-in 9
		034 ⇄ 035	Built-in 10
		036 ⇄ 037	Built-in 11
		038 ⇄ 039	Built-in 12
		040 ⇄ 041	Built-in 13
		042 ⇄ 043	Built-in 14
		044 ⇄ 045	Built-in 15
		046 ⇄ 047	Built-in 16
		048 ⇄ 049	Built-in 17
		050 ⇄ 051	Built-in 18
		052 ⇄ 053	Built-in 19
		054 ⇄ 055	Built-in 20

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
11	LED Built-in	056 ⇄ 057	Built-in 21
		058 ⇄ 059	Built-in 22
		060 ⇄ 061	Built-in 23
		062 ⇄ 063	Built-in 24
		064 ⇄ 065	Built-in 25
		066 ⇄ 067	Built-in 26
		068 ⇄ 069	Built-in 27
		070 ⇄ 071	Built-in 28
		072 ⇄ 073	Built-in 29
		074 ⇄ 075	Built-in 30
		076 ⇄ 077	Built-in 31
		078 ⇄ 079	Built-in 32
		080 ⇄ 081	Built-in 33
		082 ⇄ 083	Built-in 34
		084 ⇄ 085	Built-in 35
		086 ⇄ 087	Built-in 36
		088 ⇄ 089	Built-in 37
		090 ⇄ 091	Built-in 38
		092 ⇄ 093	Built-in 39
		094 ⇄ 095	Built-in 40
		096 ⇄ 097	Built-in 41
		098 ⇄ 099	Built-in 42
		100 ⇄ 101	Built-in 43
		102 ⇄ 103	Built-in 44
		104 ⇄ 105	Built-in 45
		106 ⇄ 107	Built-in 46
		108 ⇄ 109	Built-in 47
		110 ⇄ 111	Built-in 48
		112 ⇄ 113	Built-in 49
		114 ⇄ 115	Built-in 50
		116 ⇄ 117	Built-in 51
		118 ⇄ 119	Built-in 52
		120 ⇄ 121	Built-in 53
		122 ⇄ 123	Built-in 54
		124 ⇄ 125	Built-in 55
		126 ⇄ 127	Built-in 56
		128 ⇄ 135	Built-in 57
		136 ⇄ 137	Built-in 58
		138 ⇄ 139	Built-in 59
		140 ⇄ 141	Built-in 60
		142 ⇄ 143	Built-in 61
		144 ⇄ 145	Built-in 62
		146 ⇄ 147	Built-in 63
		148 ⇄ 149	Built-in 64
		150 ⇄ 151	Built-in 65
		152 ⇄ 153	Built-in 66
		154 ⇄ 155	Built-in 67
		156 ⇄ 157	Built-in 68
		158 ⇄ 159	Built-in 69
		160 ⇄ 161	Built-in 70
		162 ⇄ 163	Built-in 71
		164 ⇄ 165	Built-in 72
		166 ⇄ 167	Built-in 73
		168 ⇄ 169	Built-in 74
		170 ⇄ 171	Built-in 75
		172 ⇄ 173	Built-in 76
		174 ⇄ 175	Built-in 77
		176 ⇄ 177	Built-in 78
		178 ⇄ 179	Built-in 79
		180 ⇄ 181	Built-in 80
		182 ⇄ 183	Built-in 81
		184 ⇄ 185	Built-in 82
		186 ⇄ 187	Built-in 83
		188 ⇄ 189	Built-in 84
		190 ⇄ 191	Built-in 85

Channel	Function	Value	Percent/Setting
11	LED Built-in	192 ⇄ 193	Built-in 86
		194 ⇄ 195	Built-in 87
		196 ⇄ 197	Built-in 88
		198 ⇄ 199	Built-in 89
		200 ⇄ 201	Built-in 90
		202 ⇄ 203	Built-in 91
		204 ⇄ 205	Built-in 92
		206 ⇄ 207	Built-in 93
		208 ⇄ 209	Built-in 94
		210 ⇄ 211	Built-in 95
		212 ⇄ 213	Built-in 96
		214 ⇄ 215	Built-in 97
		216 ⇄ 217	Built-in 98
		218 ⇄ 219	Built-in 99
		220 ⇄ 221	Built-in 100
		222 ⇄ 223	Built-in 101
		224 ⇄ 225	Built-in 102
		226 ⇄ 227	Built-in 103
		228 ⇄ 229	Built-in 104
		230 ⇄ 231	Built-in 105
		232 ⇄ 233	Built-in 106
		234 ⇄ 235	Built-in 107
		236 ⇄ 237	Built-in 108
		238 ⇄ 239	Built-in 109
		240 ⇄ 241	Built-in 110
		242 ⇄ 243	Built-in 111
		244 ⇄ 245	Built-in 112
		246 ⇄ 247	Built-in 113
		248 ⇄ 255	Built-in 114
12	LED Built-in Speed	001 ⇄ 127	Clockwise fast to slow
		128	Stop
		128 ⇄ 255	Counter-clockwise slow to fast
13	LED Built-in Delay	000 ⇄ 255	Fast to slow
14	Background Color Macros	000	No function
		001 ⇄ 002	2700K R:156 G: 118 B: 0 W: 63
		003 ⇄ 004	3200K R:156 G: 141 B: 5 W: 89
		005 ⇄ 006	4200K R:156 G: 141 B: 14 W: 255
		007 ⇄ 008	5600K R:156 G: 207 B: 54 W: 255
		009 ⇄ 010	8000K R:130 G: 255 B: 96 W: 255
		11	Blue R: 0 G: 0 B: 255 W: 0
		012 ⇄ 048	R: 0 G: + B: 255 W: 0
		049	Cyan R: 0 G: 255 B: 255 W: 0
		050 ⇄ 086	R: 0 G: 255 B: - W: 0
		087	Green R: 0 G: 255 B: 0 W: 0
		088 ⇄ 124	R: + G: 255 B: 0 W: 0
		125	Yellow R: 255 G: 255 B: 0 W: 0
		126 ⇄ 162	R: 255 G: - B: 0 W: 0
		163	Red R: 255 G: 0 B: 0 W: 0
		164 ⇄ 200	R: 255 G: 0 B: + W: 0
		201	Magenta R: 255 G: 0 B: 255 W: 0
		202 ⇄ 238	R: - G: 0 B: 255 W: 0
		239	Blue R: 0 G: 0 B: 255 W: 0
		240 ⇄ 247	Color change, fast to slow
		248 ⇄ 255	Color jump, fast to slow
15	Background Color Dimmer	000 ⇄ 255	0-100%
16	Zoom	000 ⇄ 255	0-100%

DMX CHART



www.chauvetprofessional.com

Channel	Function	Value	Percent/Setting
17	Control	001 ⇄ 009	No function
		010 ⇄ 014	Pan/Tilt blackout
		015 ⇄ 019	No function
		020 ⇄ 024	RGBW color mixing (5 sec.)
		025 ⇄ 029	CMY color mixing (5 sec.)
		030 ⇄ 034	No function
		035 ⇄ 039	No function
		040 ⇄ 044	No function
		045 ⇄ 049	No function
		050 ⇄ 054	Pan reset
		055 ⇄ 059	Tilt reset
		060 ⇄ 064	Zoom reset
		065 ⇄ 069	No function
		070 ⇄ 074	All reset
		075 ⇄ 079	No function
		080 ⇄ 084	Pan/Tilt reverse
		085 ⇄ 089	Pan reverse
		090 ⇄ 094	Tilt reverse
		095 ⇄ 099	Cancel pan reverse
		100 ⇄ 104	Cancel tilt reverse
		105 ⇄ 109	Cancel pan/tilt reverse
		110 ⇄ 114	No function
		115 ⇄ 119	No function
		120 ⇄ 124	Fan low speed
		125 ⇄ 129	Fan full speed
		130 ⇄ 134	Fan auto
		135 ⇄ 139	Dimmer Fast mode
		140 ⇄ 144	Dimmer Smooth mode
		145 ⇄ 255	No function
18	Red (Cyan)	000 ⇄ 255	0-100%
19	Green (Magenta)	000 ⇄ 255	0-100%
20	Blue (Yellow)	000 ⇄ 255	0-100%
21	White	000 ⇄ 255	0-100%