

onAir IP Panel 2

DMX Values

32Ch

Channel	Function	Value	Percent/Setting
1	Red 1	000 ⇔ 255	0–100%
2	Fine red 1	000 ⇔ 255	0–100%
3	Green 1	000 ⇔ 255	0–100%
4	Fine green 1	000 ⇔ 255	0–100%
5	Blue 1	000 ⇔ 255	0–100%
6	Fine blue 1	000 ⇔ 255	0–100%
7	White 1	000 ⇔ 255	0–100%
8	Fine white 1	000 ⇔ 255	0–100%
9	Red 2	000 ⇔ 255	0–100%
10	Fine red 2	000 ⇔ 255	0–100%
11	Green 2	000 ⇔ 255	0–100%
12	Fine green 2	000 ⇔ 255	0–100%
13	Blue 2	000 ⇔ 255	0–100%
14	Fine blue 2	000 ⇔ 255	0–100%
15	White 2	000 ⇔ 255	0–100%
16	Fine white 2	000 ⇔ 255	0–100%
17	Red 3	000 ⇔ 255	0–100%
18	Fine red 3	000 ⇔ 255	0–100%
19	Green 3	000 ⇔ 255	0–100%
20	Fine green 3	000 ⇔ 255	0–100%
21	Blue 3	000 ⇔ 255	0–100%
22	Fine blue 3	000 ⇔ 255	0–100%
23	White 3	000 ⇔ 255	0–100%
24	Fine white 3	000 ⇔ 255	0–100%
25	Red 4	000 ⇔ 255	0–100%
26	Fine red 4	000 ⇔ 255	0–100%
27	Green 4	000 ⇔ 255	0–100%
28	Fine green 4	000 ⇔ 255	0–100%
29	Blue 4	000 ⇔ 255	0–100%
30	Fine blue 4	000 ⇔ 255	0–100%
31	White 4	000 ⇔ 255	0–100%
32	Fine white 4	000 ⇔ 255	0–100%

23Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0–100%
2	Red 1	000 ⇔ 255	0–100%
3	Green 1	000 ⇔ 255	0–100%
4	Blue 1	000 ⇔ 255	0–100%
5	White 1	000 ⇔ 255	0–100%
6	Red 2	000 ⇔ 255	0–100%
7	Green 2	000 ⇔ 255	0–100%
8	Blue 2	000 ⇔ 255	0–100%
9	White 2	000 ⇔ 255	0–100%
10	Red 3	000 ⇔ 255	0–100%
11	Green 3	000 ⇔ 255	0–100%
12	Blue 3	000 ⇔ 255	0–100%
13	White 3	000 ⇔ 255	0–100%
14	Red 4	000 ⇔ 255	0–100%
15	Green 4	000 ⇔ 255	0–100%
16	Blue 4	000 ⇔ 255	0–100%
17	White 4	000 ⇔ 255	0–100%
18	Strobe	000 ⇔ 010 011 ⇔ 255	No function Strobe, slow to fast

Channel	Function	Value	Percent/Setting
19	Color temperature	000 ⇄ 005	No function
		006 ⇄ 012	2800K
		013 ⇄ 019	2900K
		020 ⇄ 026	3000K
		027 ⇄ 033	3100K
		034 ⇄ 040	3200K
		041 ⇄ 047	3300K
		048 ⇄ 054	3400K
		055 ⇄ 061	3500K
		062 ⇄ 068	3600K
		069 ⇄ 075	3700K
		076 ⇄ 082	3800K
		083 ⇄ 089	3900K
		090 ⇄ 096	4000K
		097 ⇄ 103	4100K
		104 ⇄ 110	4200K
		111 ⇄ 117	4300K
		118 ⇄ 124	4400K
		125 ⇄ 131	4500K
		132 ⇄ 138	4600K
		139 ⇄ 145	4700K
		146 ⇄ 152	4800K
		153 ⇄ 159	4900K
		160 ⇄ 166	5000K
		167 ⇄ 173	5100K
		174 ⇄ 180	5200K
181 ⇄ 187	5300K		
188 ⇄ 194	5400K		
195 ⇄ 201	5500K		
202 ⇄ 208	5600K		
209 ⇄ 215	5700K		
216 ⇄ 222	6000K		
223 ⇄ 229	6500K		
230 ⇄ 236	7000K		
237 ⇄ 243	7500K		
244 ⇄ 255	8000K		
20	Hue	000 ⇄ 001	0
		002 ⇄ 255	-25–+25
21	Effect macros	000 ⇄ 010	No function
		011 ⇄ 039	Color chase
		040 ⇄ 068	Police car
		069 ⇄ 096	Firetruck
		097 ⇄ 125	Fire
		126 ⇄ 154	Clouds
		155 ⇄ 182	Fireworks
		183 ⇄ 211	Paparazzi
		212 ⇄ 240	Lightning
241 ⇄ 255	No function		
22	Effect macro speed	000 ⇄ 255	Speed, slow to fast

QUICK REFERENCE GUIDE



onAir IP Panel 2

Channel	Function	Value	Percent/Setting
23	Control	000 ⇔ 007	No function
		008 ⇔ 015	Reset dimmer
		016 ⇔ 023	Red shift on
		024 ⇔ 031	Red shift off
		032 ⇔ 039	S-curve dimmer
		040 ⇔ 047	Linear dimmer
		048 ⇔ 055	Square dimmer
		056 ⇔ 063	Inverse square dimmer
		064 ⇔ 071	Dimmer mode off
		072 ⇔ 079	Dimmer mode 1 (fast)
		080 ⇔ 087	Dimmer mode 2
		088 ⇔ 095	Dimmer mode 3 (slow)
		096 ⇔ 103	Fan mode auto
		104 ⇔ 111	Fan mode on
		112 ⇔ 119	Fan mode off
120 ⇔ 127	Fan mode silent		
128 ⇔ 255	Reserved for future use		

18Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0–100%
2	Red 1	000 ⇔ 255	0–100%
3	Green 1	000 ⇔ 255	0–100%
4	Blue 1	000 ⇔ 255	0–100%
5	White 1	000 ⇔ 255	0–100%
6	Red 2	000 ⇔ 255	0–100%
7	Green 2	000 ⇔ 255	0–100%
8	Blue 2	000 ⇔ 255	0–100%
9	White 2	000 ⇔ 255	0–100%
10	Red 3	000 ⇔ 255	0–100%
11	Green 3	000 ⇔ 255	0–100%
12	Blue 3	000 ⇔ 255	0–100%
13	White 3	000 ⇔ 255	0–100%
14	Red 4	000 ⇔ 255	0–100%
15	Green 4	000 ⇔ 255	0–100%
16	Blue 4	000 ⇔ 255	0–100%
17	White 4	000 ⇔ 255	0–100%
18	Strobe	000 ⇔ 010	No function
		011 ⇔ 255	Strobe, slow to fast

16Ch

Channel	Function	Value	Percent/Setting
1	Red 1	000 ⇔ 255	0–100%
2	Green 1	000 ⇔ 255	0–100%
3	Blue 1	000 ⇔ 255	0–100%
4	White 1	000 ⇔ 255	0–100%
5	Red 2	000 ⇔ 255	0–100%
6	Green 2	000 ⇔ 255	0–100%
7	Blue 2	000 ⇔ 255	0–100%
8	White 2	000 ⇔ 255	0–100%
9	Red 3	000 ⇔ 255	0–100%
10	Green 3	000 ⇔ 255	0–100%
11	Blue 3	000 ⇔ 255	0–100%
12	White 3	000 ⇔ 255	0–100%
13	Red 4	000 ⇔ 255	0–100%

Channel	Function	Value	Percent/Setting
14	Green 4	000 ⇄ 255	0–100%
15	Blue 4	000 ⇄ 255	0–100%
16	White 4	000 ⇄ 255	0–100%

15Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇄ 255	0–100%
2	Fine dimmer	000 ⇄ 255	0–100%
3	Red	000 ⇄ 255	0–100%
4	Fine red	000 ⇄ 255	0–100%
5	Green	000 ⇄ 255	0–100%
6	Fine green	000 ⇄ 255	0–100%
7	Blue	000 ⇄ 255	0–100%
8	Fine blue	000 ⇄ 255	0–100%
9	White	000 ⇄ 255	0–100%
10	Fine white	000 ⇄ 255	0–100%
11	Strobe	000 ⇄ 010	No function
		011 ⇄ 255	Strobe, slow to fast
12	Color temperature	000 ⇄ 005	No function
		006 ⇄ 012	2800K
		013 ⇄ 019	2900K
		020 ⇄ 026	3000K
		027 ⇄ 033	3100K
		034 ⇄ 040	3200K
		041 ⇄ 047	3300K
		048 ⇄ 054	3400K
		055 ⇄ 061	3500K
		062 ⇄ 068	3600K
		069 ⇄ 075	3700K
		076 ⇄ 082	3800K
		083 ⇄ 089	3900K
		090 ⇄ 096	4000K
		097 ⇄ 103	4100K
		104 ⇄ 110	4200K
		111 ⇄ 117	4300K
		118 ⇄ 124	4400K
		125 ⇄ 131	4500K
		132 ⇄ 138	4600K
		139 ⇄ 145	4700K
		146 ⇄ 152	4800K
		153 ⇄ 159	4900K
		160 ⇄ 166	5000K
167 ⇄ 173	5100K		
174 ⇄ 180	5200K		
181 ⇄ 187	5300K		
188 ⇄ 194	5400K		
195 ⇄ 201	5500K		
202 ⇄ 208	5600K		
209 ⇄ 215	5700K		
216 ⇄ 222	6000K		
223 ⇄ 229	6500K		
230 ⇄ 236	7000K		
237 ⇄ 243	7500K		
244 ⇄ 255	8000K		
13	Hue	000 ⇄ 001	0
		002 ⇄ 255	-25–+25

QUICK REFERENCE GUIDE



onAir IP Panel 2

Channel	Function	Value	Percent/Setting
14	Effect macros	000 ⇔ 010	No function
		011 ⇔ 039	Color chase
		040 ⇔ 068	Police car
		069 ⇔ 096	Firetruck
		097 ⇔ 125	Fire
		126 ⇔ 154	Clouds
		155 ⇔ 182	Fireworks
		183 ⇔ 211	Paparazzi
		212 ⇔ 240	Lightning
		241 ⇔ 255	No function
15	Effect macro speed	000 ⇔ 255	Speed, slow to fast

11Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0–100%
2	Red	000 ⇔ 255	0–100%
3	Green	000 ⇔ 255	0–100%
4	Blue	000 ⇔ 255	0–100%
5	White	000 ⇔ 255	0–100%
6	Strobe	000 ⇔ 010	No function
		011 ⇔ 255	Strobe, slow to fast
7	Color temperature	000 ⇔ 005	No function
		006 ⇔ 012	2800K
		013 ⇔ 019	2900K
		020 ⇔ 026	3000K
		027 ⇔ 033	3100K
		034 ⇔ 040	3200K
		041 ⇔ 047	3300K
		048 ⇔ 054	3400K
		055 ⇔ 061	3500K
		062 ⇔ 068	3600K
		069 ⇔ 075	3700K
		076 ⇔ 082	3800K
		083 ⇔ 089	3900K
		090 ⇔ 096	4000K
		097 ⇔ 103	4100K
		104 ⇔ 110	4200K
		111 ⇔ 117	4300K
		118 ⇔ 124	4400K
		125 ⇔ 131	4500K
		132 ⇔ 138	4600K
		139 ⇔ 145	4700K
		146 ⇔ 152	4800K
		153 ⇔ 159	4900K
		160 ⇔ 166	5000K
		167 ⇔ 173	5100K
		174 ⇔ 180	5200K
		181 ⇔ 187	5300K
		188 ⇔ 194	5400K
		195 ⇔ 201	5500K
		202 ⇔ 208	5600K
209 ⇔ 215	5700K		
216 ⇔ 222	6000K		
223 ⇔ 229	6500K		
230 ⇔ 236	7000K		

Channel	Function	Value	Percent/Setting
7	Color temperature	237 ⇄ 243	7500K
		244 ⇄ 255	8000K
8	Hue	000 ⇄ 001	0
		002 ⇄ 255	-25--+25
9	Effect macros	000 ⇄ 010	No function
		011 ⇄ 039	Color chase
		040 ⇄ 068	Police car
		069 ⇄ 096	Firetruck
		097 ⇄ 125	Fire
		126 ⇄ 154	Clouds
		155 ⇄ 182	Fireworks
		183 ⇄ 211	Paparazzi
		212 ⇄ 240	Lightning
241 ⇄ 255	No function		
10	Effect macro speed	000 ⇄ 255	Speed, slow to fast
11	Control	000 ⇄ 007	No function
		008 ⇄ 015	Reset dimmer
		016 ⇄ 023	Red shift on
		024 ⇄ 031	Red shift off
		032 ⇄ 039	S-curve dimmer
		040 ⇄ 047	Linear dimmer
		048 ⇄ 055	Square dimmer
		056 ⇄ 063	Inverse square dimmer
		064 ⇄ 071	Dimmer mode off
		072 ⇄ 079	Dimmer mode 1 (fast)
		080 ⇄ 087	Dimmer mode 2
		088 ⇄ 095	Dimmer mode 3 (slow)
		096 ⇄ 103	Fan mode auto
		104 ⇄ 111	Fan mode on
112 ⇄ 119	Fan mode off		
120 ⇄ 127	Fan mode silent		
128 ⇄ 255	Reserved for future use		

8Ch

Channel	Function	Value	Percent/Setting
1	Red	000 ⇄ 255	0–100%
2	Fine red	000 ⇄ 255	0–100%
3	Green	000 ⇄ 255	0–100%
4	Fine green	000 ⇄ 255	0–100%
5	Blue	000 ⇄ 255	0–100%
6	Fine blue	000 ⇄ 255	0–100%
7	White	000 ⇄ 255	0–100%
8	Fine white	000 ⇄ 255	0–100%

6Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇄ 255	0–100%
2	Red	000 ⇄ 255	0–100%
3	Green	000 ⇄ 255	0–100%
4	Blue	000 ⇄ 255	0–100%
5	White	000 ⇄ 255	0–100%
6	Strobe	000 ⇄ 010	No function
		011 ⇄ 255	Strobe, slow to fast

QUICK REFERENCE GUIDE



onAir IP Panel 2

5Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0–100%
2	Fine dimmer	000 ⇔ 255	0–100%
3	Color temperature	000 ⇔ 005	No function
		006 ⇔ 012	2800K
		013 ⇔ 019	2900K
		020 ⇔ 026	3000K
		027 ⇔ 033	3100K
		034 ⇔ 040	3200K
		041 ⇔ 047	3300K
		048 ⇔ 054	3400K
		055 ⇔ 061	3500K
		062 ⇔ 068	3600K
		069 ⇔ 075	3700K
		076 ⇔ 082	3800K
		083 ⇔ 089	3900K
		090 ⇔ 096	4000K
		097 ⇔ 103	4100K
		104 ⇔ 110	4200K
		111 ⇔ 117	4300K
		118 ⇔ 124	4400K
		125 ⇔ 131	4500K
		132 ⇔ 138	4600K
		139 ⇔ 145	4700K
		146 ⇔ 152	4800K
		153 ⇔ 159	4900K
		160 ⇔ 166	5000K
167 ⇔ 173	5100K		
174 ⇔ 180	5200K		
181 ⇔ 187	5300K		
188 ⇔ 194	5400K		
195 ⇔ 201	5500K		
202 ⇔ 208	5600K		
209 ⇔ 215	5700K		
216 ⇔ 222	6000K		
223 ⇔ 229	6500K		
230 ⇔ 236	7000K		
237 ⇔ 243	7500K		
244 ⇔ 255	8000K		
4	Hue	000 ⇔ 001	0
		002 ⇔ 255	-25–+25
5	Strobe	000 ⇔ 010	No function
		011 ⇔ 255	Strobe, slow to fast

4Ch

Channel	Function	Value	Percent/Setting
1	Red	000 ⇔ 255	0–100%
2	Green	000 ⇔ 255	0–100%
3	Blue	000 ⇔ 255	0–100%
4	White	000 ⇔ 255	0–100%

3Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇄ 255	0–100%
3	Color temperature	000 ⇄ 005	No function
		006 ⇄ 012	2800K
		013 ⇄ 019	2900K
		020 ⇄ 026	3000K
		027 ⇄ 033	3100K
		034 ⇄ 040	3200K
		041 ⇄ 047	3300K
		048 ⇄ 054	3400K
		055 ⇄ 061	3500K
		062 ⇄ 068	3600K
		069 ⇄ 075	3700K
		076 ⇄ 082	3800K
		083 ⇄ 089	3900K
		090 ⇄ 096	4000K
		097 ⇄ 103	4100K
		104 ⇄ 110	4200K
		111 ⇄ 117	4300K
		118 ⇄ 124	4400K
		125 ⇄ 131	4500K
		132 ⇄ 138	4600K
		139 ⇄ 145	4700K
		146 ⇄ 152	4800K
		153 ⇄ 159	4900K
		160 ⇄ 166	5000K
		167 ⇄ 173	5100K
		174 ⇄ 180	5200K
		181 ⇄ 187	5300K
		188 ⇄ 194	5400K
		195 ⇄ 201	5500K
		202 ⇄ 208	5600K
		209 ⇄ 215	5700K
		216 ⇄ 222	6000K
		223 ⇄ 229	6500K
		230 ⇄ 236	7000K
		237 ⇄ 243	7500K
		244 ⇄ 255	8000K
3	Hue	000 ⇄ 001	0
		002 ⇄ 255	-25–+25

1Ch

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇄ 255	0–100%