



## WELL Com

WELL Com makes it possible to control your W-DMX enabled lights from a smartphone or a tablet. This wireless interface hands you full control over your fixtures including the ability to build and save static looks or timed chases via a free downloadable app that supports a full universe of DMX and can save scenes and chases.

The WELL Com app is available for both Android and iOS® in both phone and tablet versions. Download Here: [Android](#) | [iOS](#)



## At a Glance

- Compact, easy-to-use battery powered Wi-Fi™ receiver and wireless WDMX™ transmitter combined with an Android™ or iOS® based control app
- 8 hours of usage on a full charge

- Compatible with Android™ and iOS® on both smartphones and tablets
- Output can be used in wireless WDMX™ or wired DMX protocols
- Full universe of DMX available for programming larger events
- Built in color picker and color macros for use with RGB, RGBA, and RGBW wash fixtures
- Program up to 24 steps per scene with selectable fade and hold times for building chases and cues
- A total of 18 scenes available for playback
- Easy to navigate user interface
- Line-of-sight distance up to 200 m

# Specifications

## Dynamic Effects

- Standalone Color Mixing: Yes
- Customizable Programs: Yes
- Recall Custom Programs: Yes

## Construction / Physical

- Dimensions: 5.13 x 3.34 x 0.98 in (130.4 x 85 x 25 mm)
- Weight: 0.6 lb (0.3 kg)
- Exterior Color: Black
- Housing Material: High-impact flame-retardant polymer

## Connections

- Power Input: Micro USB-B Male
- Data Connectors: 5-pin XLR
- Cable Length (Dmx): 17 in (0.43 m)
- Cable Length (power): 3 ft (0.91 m)

## Control

- Control Protocol: DMX, W-DMX™, Wi-fi
- DMX Channels: 512

## Electrical

- Input Voltage: 5 VDC, 1600 mA (external power supply: 100-240 VAC 47/63 Hz)
- Power and Current: 7 W, 0.125 A @ 120 V, 60 Hz
- Power and Current: 6 W, 0.078 A @ 208 V, 60 Hz
- Power and Current: 6 W, 0.075 A @ 230 V, 50 Hz

## Battery

- Battery type: Lithium Ion
- Rechargeable: Yes
- Battery Charge Time: 8 hours
- Battery Life: 8 hours
- Battery Power: 3.7 V, 6,000 mAh

## Certifications / Qualifications

- CE, FCC
- IP Rating: IP20, dry location

## What's Included

- WELL COM
- USB-A Male to Micro USB-B Male (3 ft)
- 5-pin DMX adaptor
- External power supply

## Optional Accessories

- DMX Cables

## Required Accessories

- WELL COM App available for download on iOS or Android store